



## Shared components: KNX 2 roller blinds actuator

**01524**

Smart systems&products / KNX / Shared components / DIN devices

### KNX 2 roller blinds actuator

Actuator for 2 roller shutters,  $\cos\phi$  0.6 3,5 A 250 V~ motor relay outputs, KNX standard, installation on DIN rail (60715 TH35), occupies 4 17,5 mm modules


### Product Status

2 - Will be discontinued

### Minimum order quantity

1 NR

### Alternative products



01523.1 - 250V 16A 4-output actuator KNX




### Sheets, Manuals, Documentation

- [Multilanguage instructions sheet \(543 kb\)](#)
- [Manuale installatore \(695 kb\)](#)


### Product Software

- [DB\\_ComponentiAutomazione\\_KNX\\_01.16\\_20210920.zip](#)
- [DB\\_ComponentiAutomazione\\_KNX\\_01.19\\_20230331.zip](#)


## Drawings



Space view



Backside view



3D View

## Gallery



## Technical data

- **Class group:** Installation bus systems
- **Class:** Shutting actuator for bus system
- **Bus system KNX:** Yes
- **Bus system KNX-RF (Radio Frequent):** No
- **Bus system radio frequent:** No
- **Bus system LON:** No
- **Bus system Powernet:** No
- **Other bus systems:** None
- **Radio frequent bidirectional:** No
- **Mounting method:** Other
- **Width in number of modular spacings:** 4
- **With bus connection:** Yes
- **Bus module detachable:** No
- **Local operation/hand operation:** Yes
- **With LED indication:** Yes
- **Number of inputs:** 0
- **Switching current (resistive):** 16 A
- **Max. number of venetian-blind outputs:** 2
- **With switch function:** Yes
- **Type of current:** AC
- **Degree of protection (IP):** IP20

## Certifications

- 00. CE Marking - EU
- 27. KNX ([download](#))
- 37. Marking - Morocco
- 96. Electrotechnical expert ([download](#))
- 99. WEEE Directive ([download](#))

# Packaging



**Code** 8007352383593  
**Quantity** 1 NR  
**Dim.** 11.7x10.8x7.1 [cm]  
**Weight** 254.1 [g]

# Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see [Conditions of Use](#).