



Shared components: Dimmer 0/1-10V 4 OUT 16A KNX

01550

Smart systems&products / KNX / Shared components / DIN devices

Dimmer 0/1-10V 4 OUT 16A KNX

Dimmer with 4 NO relay outputs 16 A 250 V~, 4 outputs 0/1-10 V, push buttons for local control, KNX standard, installation on DIN rail (60715 TH35), occupies 8 modules size 17.5 mm



Product Status

3 - Active

Minimum order quantity

1 NR

Sheets, Manuals, Documentation

- [Multilanguage instructions sheet \(1151 kb\)](#)
- [Installer manual \(1780 kb\)](#)
- [Installer manual \(1632 kb\)](#)

Product Software

- [DB_ComponentiAutomazione_KNX_01.16_20210920.zip](#)
- [DB_ComponentiAutomazione_KNX_01.19_20230331.zip](#)

Technical data

- **Class group:** Installation bus systems
- **Class:** Light control unit for bus system
- **Bus system KNX:** Yes
- **Bus system KNX-RF (Radio Frequent):** No
- **Bus system radio frequent:** No
- **Bus system LON:** No
- **Bus system Powernet:** No
- **Other bus systems:** None
- **Radio frequent bidirectional:** No
- **Mounting method:** DRA (DIN-rail adapter)
- **Width in number of modular spacings:** 6
- **With bus connection:** Yes
- **Local operation/hand operation:** Yes
- **With LED indication:** Yes
- **Max. switching current (resistive load):** 10 A
- **Number of outputs:** 4

Certifications

- 00. CE Marking - EU
- 27. KNX ([download](#))
- 43. UKCA mark - Great Britain
- 46. UK PSTI compliance
- 99. WEEE Directive ([download](#))

Packaging



Code 8007352657458
Quantity 1 NR
Dim. 22x9.2x6.6 [cm]
Weight 698.6 [g]

Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see [Conditions of Use](#).