ARKÉ: MASTER dimmer 120V Metal

19135.1.120.M

Wiring devices / Traditional wiring devices / ARKÉ / Devices

MASTER dimmer 120V Metal

Universal-dimmer 120 V~ 60 Hz, phase-cutting, for: 40-400 W incandescent lamps, 40-300 VA electronic transfomers, 10-200 W CFL lamps, 3-200 W LED lamps, LED phase-cutting electronic transfomers, ON/OFF control and built-in or from NO peripheral push buttons regulation, MASTER function for 19137.120, minimum brightness regulation, visible in darkness, Metal. Not for Isoset enclosures

Product Status

3 - Active

Minimum order quantity

1 NR

Sheets, Manuals, Documentation

- Light Multilanguage instructions sheet (1283 kb)
- Full Multilanguage instructions sheet (1406 kb)
- Multilanguage instructions sheet (2498 kb)

Video

- Arké lives in your time

Technical data

- **Class group**: Domestic switching devices
- **Class**: Dimmer
- **Method of operation**: Turn button
- **Mounting method**: Flush-mounted
- **Material**: Plastic
- **Material quality**: Thermoplastic
- **Surface protection**: Lacquered
- **Surface finishing**: Matt
- **Colour**: Aluminium
- **RAL-number (similar)**: 9007
- **Transparent**: No
- **Nominal voltage**: 120,00 - 120,01 V
- **Connection type**: Screwed terminal
- **Device width**: 22,30 mm
- **Device height**: 49,00 mm
- **Device depth**: 50,70 mm

Certifications

- 00. CE Marking - EU
- 37. Marking - Morocco
- 43. UKCA mark - Great Britain
- 96. Electrotechnical expert (download)
- 99. WEEE Directive (download)

Packaging

Code	8007352601420	**Code**	8007352603479
Quantity	1 NR	**Quantity**	10 NR
Dim.	5.1x4.3x5.3 [cm]	**Dim.**	26.9x11.6x4.9 [cm]
Weight	54.2 [g]	**Weight**	606 [g]

Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported.Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed.For the terms of use of the information on the product info sheet see Conditions of Use.