



ARKÉ: SLAVE dimmer 230V grey

19137

Wiring devices / Traditional wiring devices / ARKÉ / Devices

SLAVE dimmer 230V grey

SLAVE dimmer 230 V~ 50 Hz for: 40-500 W incandescent lamps, 40-300 VA electronic transformers, 10-200 W CFL lamps, 3-200 W LED lamps, control from MASTER dimmer with bleeder (01873), grey. Not for IsoSet enclosures

Product Status

2 - Will be discontinued

Minimum order quantity

5 NR


Sheets, Manuals, Documentation

- [FI - Foglio istruzioni ZIS_49400569A0 \(2910 kb\)](#)
- [Installation diagrams \(2458 kb\)](#)


Video

- [New universal dimmers](#)
- [Arké lives in your time](#)


Drawings



Space view



Backside view



3D View



Gallery



Technical data

- **Class group:** Domestic switching devices
- **Class:** Dimmer
- **Method of operation:** Other
- **Type of load:** Universal and LED Retrofit
- **Applicable with button:** No
- **Applicable with movement sensor:** No
- **Applicable with presence indicator:** No
- **Applicable with time switch/timer:** No
- **Applicable with transmission button:** No
- **Applicable with infrared button:** No
- **Mounting method:** Flush-mounted
- **Type of fastening:** Snapper mounting
- **Material:** Plastic
- **Material quality:** Thermoplastic
- **Surface protection:** Untreated
- **Surface finishing:** Matt
- **Colour:** Grey
- **RAL-number (similar):** 7015
- **Transparent:** No
- **Suitable for degree of protection (IP):** IP40
- **Nominal voltage:** 230,00 - 230,01 V
- **Frequency:** 50,00 - 50,01 HZ
- **Control voltage:** 230,00 - 230,01 V
- **Device width:** 22,30 mm
- **Device height:** 49,00 mm
- **Device depth:** 51,00 mm

Certifications

- 37. Marking - Morocco
- 96. Electrotechnical expert ([download](#))

Packaging



Code 8007352459687
Quantity 1 NR
Dim. 5.1x4.3x5.3 [cm]
Weight 57.4 [g]



Code 8007352459694
Quantity 5 NR
Dim. 14.4x11.6x6 [cm]
Weight 333 [g]

Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see [Conditions of Use](#).