



ARKÉ: TV-FM-SAT single conn. 3outs Metal

19303.M

Wiring devices / Traditional wiring devices / ARKÉ / Devices

TV-FM-SAT single conn. 3outs Metal

Coaxial TV-FM radio-SAT 5-2400 MHz socket outlet, single connection, demix, 3 outputs with TV male and female FM radio and F-type (SAT) connectors, connection attenuation 1 dB, Metal - 2 modules. Allows the passage of d.c. current and control signals (24 V 500 mA max) through the female connector

Product Status

3 - Active

Minimum order quantity

5 NR


Sheets, Manuals, Documentation

- [Multilanguage instructions sheet \(485 kb\)](#)


Video

- [Arké lives in your time](#)


Drawings



Space view



Backside view



3D View



Technical data

- **Class group:** Antenna and satellite technique
- **Class:** Antenna socket box
- **Model:** End socket
- **Cover:** None
- **Tap loss at 860 MHz:** 1,80 dB
- **Tap loss at 2150 MHz:** 1,30 dB
- **Number of outlets:** 3
- **Suitable for remote power supply:** Yes
- **Type of fastening:** Snap mounting (engagement)
- **Colour:** Aluminium
- **RAL-number (similar):** 9007
- **Surface protection:** Lacquered
- **Material:** Plastic

Certifications

- 00. CE Marking - EU
- 10. EAC Eurasian Customs Union
- 37. Marking - Morocco
- 43. UKCA mark - Great Britain
- 96. Electrotechnical expert ([download](#))
- 99. WEEE Directive ([download](#))

Packaging



8 007352 600669

Code 8007352600669
Quantity 1 NR
Dim. 5.1x4.3x5.3 [cm]
Weight 82.4 [g]



8 007352 602472

Code 8007352602472
Quantity 5 NR
Dim. 14.4x11.6x6 [cm]
Weight 460.9 [g]

Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see [Conditions of Use](#).