



## ARKÉ: Vertical pocket badge switch white

### 19465.B

Wiring devices / Traditional wiring devices / ARKÉ / Devices

### Vertical pocket badge switch white

Electronic badge switch with vertical pocket, 16 A 250 V~ change-over relay output, supply voltage 230 V~ 50-60 Hz, 24 V~ 50-60 Hz and 24 Vdc (SELV), white - 3 modules. Provided without ISO card (badge)



### Product Status

3 - Active

### Minimum order quantity

1 NR


### Sheets, Manuals, Documentation

- [Light Multilanguage instructions sheet \(749 kb\)](#)
- [Full Multilanguage instructions sheet \(816 kb\)](#)


### Video

- [Arké lives in your time](#)


### Drawings



Space view



Backside view



3D View

## Gallery



## Technical data

- **Class group:** Alarm installations, emergency call and signalling
- **Class:** Access control system
- **Standalone:** Yes
- **Networkable:** No
- **PC-binding:** No
- **Type of interface:** None
- **Reading strategy:** Data medium
- **Signalling:** None
- **Mounting method:** Flush-mounted
- **Operating voltage AC 50 Hz:** 250,00 - 250,01 V
- **Operating voltage AC 60 Hz:** 250,00 - 250,01 V
- **Operating voltage DC:** 24,00 - 24,01 V
- **Operating temperature:** 5 - 45 °C
- **Degree of protection (IP):** IP20
- **Colour:** White
- **Material:** Plastic
- **Width:** 67,50 mm
- **Height:** 49,00 mm
- **Depth:** 56,80 mm

## Certifications

- 00. CE Marking - EU
- 37. Marking - Morocco
- 37. Marking - Morocco
- 43. UKCA mark - Great Britain
- 96. Electrotechnical expert ([download](#))
- 99. WEEE Directive ([download](#))

## Packaging



**Code** 8007352456587  
**Quantity** 1 NR  
**Dim.** 5.7x5.3x7.7 [cm]  
**Weight** 87.7 [g]



**Code** 8007352738379  
**Quantity** 5 NR  
**Dim.** 21.4x11.6x6 [cm]  
**Weight** 495.3 [g]



**Code** 8007352738386  
**Quantity** 50 NR  
**Dim.** 30.5x25.5x22.5 [cm]  
**Weight** 5,293 [g]

## Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see [Conditions of Use](#).