



## EIKON: MASTER dimmer 120-230V Next

---

### 20148.N

Wiring devices / Traditional wiring devices / EIKON / Devices

### MASTER dimmer 120-230V Next

Dimmer, supply voltage 120-230 V~ 50-60 Hz for: 40-500/40-800 W incandescent lamps and 40-300/40-500 VA ferromagnetic transformers, control and regulation with built-in or from peripheral NO push buttons, MASTER function, TRIAC technology, visible in darkness, Next

### Product Status

2 - Will be discontinued


### Minimum order quantity

10 NR

### Sheets, Manuals, Documentation

- [Multilanguage instructions sheet \(270 kb\)](#)

### Drawings



Backside view




## Technical data

- **Class group:** Domestic switching devices
- **Class:** Dimmer
- **Method of operation:** Push button
- **Type of load:** Inductive load
- **Applicable with button:** Yes
- **Applicable with movement sensor:** No
- **Applicable with presence indicator:** No
- **Applicable with time switch/timer:** No
- **Applicable with transmission button:** No
- **Applicable with infrared button:** No
- **Mounting method:** Flush-mounted
- **Type of fastening:** Snapper mounting
- **Material:** Plastic
- **Material quality:** Thermoplastic
- **Surface protection:** Lacquered
- **Surface finishing:** Matt
- **Colour:** Silver
- **RAL-number (similar):** 9022
- **Transparent:** No
- **Suitable for degree of protection (IP):** IP40
- **Nominal voltage:** 120,00 - 230,00 V
- **Frequency:** 50,00 - 60,00 HZ
- **Control voltage:** 120,00 - 230,00 V
- **Device width:** 22,30 mm
- **Device height:** 49,00 mm
- **Device depth:** 52,40 mm

## Certifications

- 00. CE Marking - EU
- 43. UKCA mark - Great Britain
- 99. WEEE Directive ([download](#))

## Packaging



**Code** 8007352291249  
**Quantity** 1 NR  
**Dim.** 5.1x4.3x5.3 [cm]  
**Weight** 52.53 [g]

**Code** 8007352291256  
**Quantity** 10 NR  
**Dim.** 26.9x11.6x4.9 [cm]  
**Weight** 589.07 [g]

## Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see [Conditions of Use](#).