



## Shared components: MASTER dimmer 120V spare part

### R01870.120

Smart systems&products / By-me Plus / Shared components / DIN devices

### MASTER dimmer 120V spare part

Spare 120 V~ 60 Hz MASTER dimmer for 40-500 W incandescent lamps, 40-300 VA electronic transformers, 10-200 W CFL lamps, 3-200 W LED lamps for LED electronic power supply units, protection fuse, installation on DIN rail (60715 TH35), occupies 4 modules size 17.5 mm

### Product Status

3 - Active

### Minimum order quantity

1 NR

## Technical data

- **Class group:** Installation bus systems
- **Class:** Dimming actuator for bus system
- **Bus system KNX:** No
- **Bus system KNX-RF (Radio Frequent):** No
- **Bus system radio frequent:** No
- **Bus system LON:** No
- **Bus system Powernet:** No
- **Other bus systems:** Other
- **Radio frequent bidirectional:** No
- **Model:** Dimming actuator
- **Mounting method:** Other
- **Width in number of modular spacings:** 4
- **With bus connection:** Yes
- **Bus module detachable:** No
- **Local operation/hand operation:** No
- **With LED indication:** Yes
- **Number of outputs:** 1
- **Output power:** 40 - 500 W
- **Power boost suitable:** No
- **Type of load:** Universal and LED Retrofit
- **Voltage:** 120,00 - 120,01 V
- **Parallel-service possible:** No
- **Frequency:** 60,00 - 60,01 HZ
- **Degree of protection (IP):** IP20



**VIMAR**

## Certifications

- 00. CE Marking - EU
- 43. UKCA mark - Great Britain
- 99. WEEE Directive ([download](#))

# Packaging



**Code** 8007352648623  
**Quantity** 1 NR  
**Dim.** 11.7x10.8x7.1 [cm]  
**Weight** 226.9 [g]

# Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see [Conditions of Use](#).