



## Shared components: MASTER dimmer 230V spare part

### R01870

Smart systems&products / By-me Plus / Shared components / DIN devices

#### MASTER dimmer 230V spare part

Spare 230 V~ 50/60 Hz MASTER dimmer for 40-500 W incandescent lamps, 40-300 VA electronic transformers, 10-200 W CFL lamps, 3-200 W LED lamps, for LED electronic power supply units, protection fuse, installation on DIN rail (60715 TH35), occupies 4 modules size 17.5 mm



3 - Active

1 NR

- [By-me automation-fw Compatibility \(206 kb\)](#)
- [Installation diagrams \(2458 kb\)](#)

- **Class group:** Installation bus systems
- **Class:** Dimming actuator for bus system
- **Bus system KNX:** No
- **Bus system KNX-RF (Radio Frequent):** No
- **Bus system radio frequent:** No
- **Bus system LON:** No
- **Bus system Powernet:** No
- **Other bus systems:** Other
- **Radio frequent bidirectional:** No
- **Model:** Dimming actuator
- **Mounting method:** Other
- **Width in number of modular spacings:** 4
- **With bus connection:** Yes
- **Bus module detachable:** No
- **Local operation/hand operation:** No
- **With LED indication:** Yes
- **Number of outputs:** 1
- **Output power:** 40 - 500 W
- **Power boost suitable:** No
- **Type of load:** Universal and LED Retrofit
- **Voltage:** 230,00 - 230,01 V
- **Parallel-service possible:** No
- **Frequency:** 50,00 - 60,00 HZ
- **Degree of protection (IP):** IP20

- 00. CE Marking - EU
- 43. UKCA mark - Great Britain

- 99. WEEE Directive ([download](#))



8007352648616  
1 NR  
11.7x10.8x7.1 [cm]  
228.8 [g]

Vimar