



## NEVE UP: Two 2P+E 15A outlets USA+GFCI car.matt

**00296.CM**

Wiring devices / Traditional wiring devices / NEVE UP / Devices

### Two 2P+E 15A outlets USA+GFCI car.matt

Two 2P+T 15 A 125 V~ 60 Hz American standard socket outlets with Ground Fault Circuit Interrupter (GFCI), device complete with mounting frame, to be completed with 3-module Plana or Neve Up cover plates, carbon matt


### Product Status

3 - Active


### Minimum order quantity

5 NR


### Drawings



Space view



Backside view



3D View




## Technical data

- **Class group:** Domestic switching devices
- **Class:** Socket outlet
- **Number of modules (module system):** 3
- **With hinged lid:** No
- **Label space/information surface:** Yes
- **Colour:** Anthracite
- **RAL-number (similar):** 7016
- **Metallic colour:** No
- **Transparent:** No
- **Lockable:** No
- **Eject-mechanism:** No
- **Insulated mounting:** No
- **With miniature fuse:** No
- **Mounting method:** Flush-mounted
- **Type of fastening:** Mounting with screw
- **Material:** Plastic
- **Material quality:** Thermoplastic
- **Surface protection:** Lacquered
- **Surface finishing:** Matt
- **Anti-bacterial treatment:** No
- **With loop through function:** No
- **With on/off switch:** No
- **Rotated central insert:** No
- **Nominal current:** 15 A
- **Nominal voltage:** 125 V
- **Frequency:** 60,00 - 60,01 HZ
- **Rated fault current:** 6 mA
- **Device depth:** 41,10 mm

## Certifications

- 00. CE Marking - EU
- 19. NOM - Mexico
- 29. QCERT - Colombia ([download](#))
- 37. Marking - Morocco

## Packaging



**Code** 8007352667327  
**Quantity** 1 NR  
**Dim.** 6.7x5.2x12 [cm]  
**Weight** 162.97 [g]



**Code** 8007352667334  
**Quantity** 5 NR  
**Dim.** 29.5x13.5x7.7 [cm]  
**Weight** 889.85 [g]



**Code** 8007352667341  
**Quantity** 95 NR  
**Dim.** 55.5x37.5x29 [cm]  
**Weight** 17,787.15 [g]

## Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see [Conditions of Use](#).