



Adaptors: S31 multi-adaptor +2P17/11+P30 out.black

00325

Portable installation / Plugs and socket outlets / Adaptors / Residential adaptors

S31 multi-adaptor +2P17/11+P30 out.black

SICURY 250 V~ multiway adaptor, black - max load 1500 W - 2P+E 16 A plug, German/French standards - two 2P+E 16 A Bpresa socket outlets, Italian standard P17/11 and one 2P+E 16 A socket outlet, Italian standard P30 (lateral and central earth contacts)



Product Status

3 - Active

Minimum order quantity 25 NR

You may also be interested in



00325.B - S31 multi-adaptor +2P17/11+P30 out.white

Technical data

- Class group: Domestic switching devices
- Class: Plug adapter
- Model: Compact
- With plug for AU/NZ/PG/AR (AS/NZS 3112) (type I): No
- With plug for BE/DE/NL/RU (protective contact CEE 7/4, type F): Yes
- With plug for FR (earth pin) (type E): Yes
- With plug for UK/HK (BS 1363) (type G): No
- With plug for IT (S/P 11): No

Certifications

- 00. CE Marking EU
- 01. IMQ Italy (download)
- 10. EAC Eurasian Customs Union

Packaging





Code 8007352066977 Quantity 1 NR 14x6x4.6 [cm] Dim. 72.73 [g] Weight

Quantity 25 NR 27x26x16 [cm] Weight 2,083 [g]

Dim.

Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported.Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed.For the terms of use of the information on the product info sheet see Conditions of Use.

- With plug for IT (S/P 17) (type L): No
- With plug for US/CA/CN (NEMA 1-15) (type A): No
- With plug for US/CA/CN (NEMA 5-15) (type B): No
- Type of bus: Other
- Number of USB ports: 0
- Colour: Black
- Nominal voltage: 230,00 230,01 V
- Nominal current: 0,00 16,00 A
- 37. Marking Morocco
- 98. Warning for adapters (download)
- 99. WEEE Directive (download)