



## Multiple socket outlets: Multi-outlet 4P17/11+S31 plug black

### 00404.K

Portable installation / Plugs and socket outlets / Multiple socket outlets / 400 series multiple sockets

### Multi-outlet 4P17/11+S31 plug black

2P+E 16 A 250 V~ multiple portable socket outlet, black: 4 SICURY Bpresa outlets, Italian standard P17/11, 1,5 m 3G1 mm<sup>2</sup> cable and 2P+E 16 A plug, German/French standards, 90° cable entry



### Product Status

2 - Will be discontinued

### Minimum order quantity

20 NR

## Technical data

- **Class group:** Domestic switching devices
- **Class:** Socket outlet combination
- **Housing shape:** Rectangular
- **Number of socket outlets CEE 7/16 (EURO):** 0
- **Number of socket outlets with protective contact CEE 7/3 (type F):** 0
- **Number of socket outlets with earth pin:** 0
- **Number of cold device socket outlets:** 0
- **Number of socket outlets Italian standard type Bipasso:** 4
- **Number of socket outlets Italian standard type P11:** 0
- **Number of NEMA-outlets:** 0
- **With on/off switch:** No
- **Residual current circuit breaker (RCCB):** No
- **Mains filter:** No
- **Number of other socket outlets:** 0
- **Over voltage protection:** No
- **Nominal current:** 16 A
- **With cover:** No
- **Material:** Plastic
- **Material quality:** Thermoplastic
- **Halogen free:** Yes
- **Surface protection:** Untreated
- **Surface finishing:** Glossy
- **Colour:** Black
- **RAL-number (similar):** 9005
- **Transparent:** No
- **Degree of protection (IP):** IP20
- **Rotated central insert:** No
- **NEMA designation:** None

## Certifications

- 37. Marking - Morocco

# Packaging



**Code** 8007352144446  
**Quantity** 1 NR  
**Dim.** 24x6x3 [cm]  
**Weight** 264.07 [g]

**Code** 8007352144453  
**Quantity** 20 NR  
**Dim.** 39.5x30x17 [cm]  
**Weight** 5,701.33 [g]

# Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see [Conditions of Use](#).