



# Portable plugs&socket outlets: 2P 10A P10 axial outlet black

### 01022

Portable installation / Plugs and socket outlets / Portable plugs&socket outlets / Mille series plugs&sockets

### 2P 10A P10 axial outlet black

2P 10 A 250 V~ SICURY socket outlet, Italian standard P10, axial cable entry, black

#### **Product Status**

3 - Active

## Minimum order quantity

100 NR

# You may also be interested in



01022.B - 2P 10A P10 axial outlet white



### Technical data

Class group: Domestic switching devices

Class: Socket outletModel: Italian type P10With signal lamp: NoNumber of units: 1

Number of modules (module system): 0Number of socket outlets switchable: 0

Connection type: Screwed terminal

With hinged lid: No

With enhanced contact protection: Yes Label space/information surface: Yes

Colour: Black

RAL-number (similar): 9005

Metallic colour: NoTransparent: NoLockable: Yes

Eject-mechanism: No
Insulated mounting: No
With function lighting: No
With orientation lighting: No
Over voltage protection: No

Fault current protection: No
With miniature fuse: No

Special power supply: Other Mounting method: Other

Type of fastening: Mounting with screw

Material: Plastic

Material quality: Thermoplastic

**Halogen free**: Yes

Surface protection: Untreated

**Surface finishing**: Matt

Anti-bacterial treatment: NoWith loop through function: No

With on/off switch: No
 Rotated central insert: No
 Nominal current: 10 A
 Nominal voltage: 250 V
 Frequency: 50,00 - 60,00 HZ

Suitable for degree of protection (IP): IP20

Device width: 40,00 mm Device height: 46,00 mm Device depth: 18,00 mm

### Certifications

00. CE Marking - EU

• 01. IMQ - Italy (download)

10. EAC Eurasian Customs Union

37. Marking - Morocco

99. WEEE Directive (download)

## Packaging



Code Quantity Dim. Weight 8007352035324

4x6.6x1.8 [cm] 26.26 [g]



Code Quantity Dim. Weight 8007352325753 10 NR 20x15x5 [cm] 262.6 [g]



Code Quantity Dim. Weight 8007352007413 100 NR 28.5x26x23.5 [cm] 2,822.2 [g]

## Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see Conditions of Use.