



## Shared components: Home autom.dimmer 2OUT200W LED120-240V

**01418**

Smart systems&products / By-me Plus / Shared components / DIN devices

### Home autom.dimmer 2OUT200W LED120-240V

Dimmer, 120-240 V~ 50/60 Hz, cutting-edge phase, 2 outputs for 40-300 W at 240 V~, 20-150 W at 120 V~ incandescent lamps, 40-300 VA at 240 V~, 20-150 VA at 120 V~ electronic transformers, CFL 10-200 W at 240 V~, 5-100 W at 120 V~ CFL lamps, 3-200 W at 240 V~, 3-100 W at 120 V~ LED lamps, local control push button, By-me Plus smart automation, fuse protection, on DIN (60715 TH35) rail installation, occupies 4 17.5 mm modules



### Product Status

3 - Active


### Minimum order quantity

1 NR

### Sheets, Manuals, Documentation

- [Notice technique \(527 kb\)](#)
- [Ficha de instrucciones \(526 kb\)](#)
- [Φυλλάδιο οδηγιών \(644 kb\)](#)
- [Anweisungsblatt \(528 kb\)](#)
- [Instructions sheet \(512 kb\)](#)
- [\(562 kb\)](#)
- [Foglio istruzioni \(477 kb\)](#)


## Drawings



Space view



Backside view



3D View


## Technical data

- **Class group:** Installation bus systems
- **Class:** Power supply for bus system
- **Bus system KNX:** No
- **Bus system KNX-RF (Radio Frequent):** No
- **Bus system radio frequent:** No
- **Bus system LON:** No
- **Bus system Powernet:** No
- **Other bus systems:** Other
- **Mounting method:** DRA (DIN-rail adapter)
- **Width in number of modular spacings:** 4
- **With LED indication:** Yes
- **Bus voltage stockable:** No
- **Number of integrated choke coils:** 0
- **Number of lines to feed:** 2
- **Max. output current:** 2,70 mA

## Certifications

- 00. CE Marking - EU
- 37. Marking - Morocco
- 43. UKCA mark - Great Britain
- 92. RoHS UAE
- 99. WEEE Directive ([download](#))

## Packaging



**Code** 8007352613447  
**Quantity** 1 NR  
**Dim.** 11.7x10.8x7.1 [cm]  
**Weight** 210.1 [g]

## Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see [Conditions of Use](#).