



Surface mounting components: By-alarm - 24-zone control unit 120V~

01700.120

Safety / By-alarm Plus / Surface mounting components / Non-modular components

By-alarm - 24-zone control unit 120V~

By-alarm programmable control panel that can be managed via display keyboard, power supply 120 V~ 60 Hz, 8 local inputs expandable to 24 via the expansion modules, 1 power supply output 13.8 Vdc 1.5 A expandable with additional power supply unit, 1 alarm relay output, 1 change-over relay output 3 A 24 V~ expandable with another 24 via expansion modules, complete with metal enclosure, surface mounting



Product Status

2 - Will be discontinued

Minimum order quantity

1 NR

Sheets, Manuals, Documentation

- [Multilanguage instructions sheet \(523 kb\)](#)
- [Installer manual \(4411 kb\)](#)
- [Programming manual \(1832 kb\)](#)

Product Software

- [SW_By-alarmManager-EN_REL-02.01_20201127.zip](#)

Video

- [Integration with burglar alarm system](#)

Drawings

Technical data

- **Class group:** Alarm installations, emergency call and signalling
- **Class:** Central alarm panel for intrusion detection system
- **Number of detection groups:** 24
- **Integrated dial device:** No
- **Number of outputs for acoustic signal generators:** 2
- **Occurrence memory:** Yes
- **Operating voltage:** 120 V
- **Suitable for bus connection:** Yes
- **Radio connection:** No
- **With power adaptor:** Yes
- **Emergency power supply integrated:** Yes
- **Interface external:** Yes
- **Height:** 35.300,00 mm
- **Width:** 32.500,00 mm
- **Depth:** 12.600,00 mm

Certifications

- 00. CE Marking - EU
- 19. NOM - Mexico
- 37. Marking - Morocco
- 43. UKCA mark - Great Britain
- 99. WEEE Directive ([download](#))

Packaging



Code 8007352548084
Quantity 1 NR
Dim. 37.5x33.5x13 [cm]
Weight 5,513 [g]

Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see [Conditions of Use](#).