Shared components: Relay actuator

01850.2

Smart systems&products / By-me Plus / Shared components / DIN devices

Relay actuator

Actuator with 16 A 120-230 V~ change-over relay output, with circulation pump function, push button for manual operating, on DIN (60715 TH35) rail installation, occupies 2 17,5 mm modules, RAL 7035 grey

Product Status

3 - Active

Minimum order quantity

1 NR

Sheets, Manuals, Documentation

- Multilanguage instructions sheet (1586 kb)
- By-me automation-fw Compatibility (206 kb)

Video

- Single-phase load control system with ph

Drawings



Space view

Backside view



3D View

Technical data

- **Class group**: Installation bus systems
- **Class**: Switch actuator for bus system
- **Bus system KNX**: No
- **Bus system KNX-RF (Radio Frequent)**: No
- **Bus system radio frequent**: No
- **Bus system LON**: No
- **Bus system Powernet**: No
- **Other bus systems**: Other
- **Radio frequent bidirectional**: No
- **Mounting method**: Other
- **Width in number of modular spacings**: 2
- **Local operation/hand operation**: Yes
- **With LED indication**: Yes
- **Suitable for C-load**: No
- **Max. number of switching contacts**: 1
- **Rated current**: 16 A
- **Rated operating voltage**: 120,00 - 230,00 V
- **Different phases connectable**: No
- **With bus connection**: Yes
- **Modular expandability**: No
- **Degree of protection (IP)**: IP20

Certifications

- 00. CE Marking - EU
- 01. IMQ - Italy (download)
- 37. Marking - Morocco
- 43. UKCA mark - Great Britain
- 92. RoHS UAE
- 96. Electrotechnical expert (download)
- 99. WEEE Directive (download)

Packaging

8 0 0 7 3 5 2 3 6 9 2 3 8

Code 8007352369238
Quantity 1 NR
Dim. 14.2x6.7x5.9 [cm]
Weight 120 [g]

Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported.Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed.For the terms of use of the information on the product info sheet see Conditions of Use.