



Shared components: SLAVE dimmer 230V 500VA

01868

Smart systems&products / By-me Plus / Shared components / DIN devices

SLAVE dimmer 230V 500VA

SLAVE dimmer, 230 V~, for: 40-500 VA to 50 Hz, 40-400 VA to 60 Hz electronic transformers, with neutral terminals, control from 01867, MOSFET technology, protection fuse, for DIN (60715 TH35)rail installation, occupies 4 17,5 mm modules

Product Status

2 - Will be discontinued

Minimum order quantity

1 NR

Sheets, Manuals, Documentation

- [FI - Foglio istruzioni ZIS_49400260A0 \(573 kb\)](#)



Technical data

- **Class group:** Installation bus systems
- **Class:** Dimming actuator for bus system
- **Bus system KNX:** No
- **Bus system KNX-RF (Radio Frequent):** No
- **Bus system radio frequent:** No
- **Bus system LON:** No
- **Bus system Powernet:** No
- **Other bus systems:** Other
- **Radio frequent bidirectional:** No
- **Model:** Dimming actuator
- **Mounting method:** Other
- **Width in number of modular spacings:** 4
- **With bus connection:** No
- **Bus module detachable:** No
- **Local operation/hand operation:** No
- **With LED indication:** Yes
- **Number of outputs:** 1
- **Power boost suitable:** Yes
- **Type of load:** Universal
- **Voltage:** 230,00 - 230,01 V
- **Parallel-service possible:** No
- **Frequency:** 50,00 - 60,00 HZ
- **Degree of protection (IP):** IP20

Certifications

- 00. CE Marking - EU
- 37. Marking - Morocco
- 43. UKCA mark - Great Britain
- 96. Electrotechnical expert ([download](#))
- 99. WEEE Directive ([download](#))

Packaging



Code 8007352387492
Quantity 1 NR
Dim. 11.7x10.8x7.1 [cm]
Weight 203.2 [g]

Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see [Conditions of Use](#).