



Shared components: Multifunct.autom.actuator 4OUT MARINE

01974

Smart systems&products / By-me Plus / Shared components / DIN devices

Multifunct.autom.actuator 4OUT MARINE

Actuator with 4 16 A 120-230 V~ change-over relay outputs, programmable function for lighting, rolling shutters laths orientation, fan-coil and push button control, By-me automation, for DIN (60715 TH35) rail installation, occupies 4 17,5 mm modules. For MARINE sector

Product Status

3 - Active

Minimum order quantity

1 NR

Sheets, Manuals, Documentation

- [FI - Foglio istruzioni ZIS_49400841A0 \(488 kb\)](#)
- [By-me automation-fw Compatibility \(206 kb\)](#)

Drawings

Technical data

- **Class group:** Installation bus systems
- **Class:** Switch actuator for bus system
- **Bus system KNX:** No
- **Bus system KNX-RF (Radio Frequent):** No
- **Bus system radio frequent:** No
- **Bus system LON:** No
- **Bus system Powernet:** No
- **Other bus systems:** Other
- **Radio frequent bidirectional:** No
- **Width in number of modular spacings:** 4
- **Local operation/hand operation:** No
- **With LED indication:** Yes
- **Suitable for C-load:** No
- **Max. number of switching contacts:** 4
- **Rated current:** 16 A
- **Rated operating voltage:** 120,00 - 230,00 V
- **Different phases connectable:** No
- **With bus connection:** Yes
- **Modular expandability:** No
- **Degree of protection (IP):** IP20




Certifications

- 00. CE Marking - EU
- 37. Marking - Morocco
- 43. UKCA mark - Great Britain
- 96. Electrotechnical expert ([download](#))
- 99. WEEE Directive ([download](#))

Packaging



8 007352 539532



8 007352 573178

Code 8007352539532
Quantity 1 NR
Dim. 11.7x10.8x7.1 [cm]
Weight 243.2 [g]

Code 8007352573178
Quantity 60 NR
Dim. 59x38.5x30 [cm]
Weight 14,580 [g]

Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see [Conditions of Use](#).