



Shared components: 1P NO 24V 6-button control 3M

02687

Wiring devices / Traditional wiring devices / Shared components / Devices

1P NO 24V 6-button control 3M

Product Status

3 - Active


Minimum order quantity

10 NR


Sheets, Manuals, Documentation

- Light multilanguage instructions sheet (540 kb)
- Full multilanguage instructions sheet (1010 kb)

Drawings








Backside view





3D View

Technical data

Class group: Domestic switching devices

Class: Push button

Assembly arrangement: Modular device for domestic switching devices

Model: Group push button

Method of operation: Push button

Number of contacts as normally closed contact: 0

Number of contacts as normally open contact: 6

Number of contacts as change-over contact: 0

Number of revolving contacts: 0

Contactless type: No Number of rockers: 6

Number of modules (module system): 300

Nominal voltage: 24 V Rated current: 50,00 A With lighting: Yes With light source: No With signal lamp: No

Feedback-signal contact: No

Connection type: Other

Mounting method: Built-in installation

Type of fastening: Other

Material: Plastic

Material quality: Thermoplastic

Halogen free: Yes

Anti-bacterial treatment: No Surface protection: Other Surface finishing: Matt

Colour: Other

RAL-number (similar): 9004

Transparent: No

Label space/information surface: Yes

Imprint: None

Suitable for degree of protection (IP): IP20

Impact strength: Other Device width: 67,30 mm Device height: 49,00 mm Device depth: 22,20 mm

Compatible with Apple HomeKit: No Compatible with Google Assistant: No Compatible with Amazon Alexa: No

IFTTT support available: No

Certifications

00. CE Marking - EU

00. CE Marking - EU

37. Marking - Morocco

43. UKCA mark - Great Britain

92. RoHS UAE

99. WEEE Directive (download)

Packaging



Code Quantity Weight

8007352712287

5.3x3.9x7.6 [cm] 43.19 [g]



Code Quantity Dim. Weight

8007352712294 10 NR 28.1x13.1x6 [cm] 506.89 [g]

Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see Conditions of Use.