



Surface mounting components: By-alarm Plus power unit 230V13Vdc6,2A

03806

Safety / By-alarm Plus / Surface mounting components / Non-modular components

By-alarm Plus power unit 230V13Vdc6,2A

By-alarm Plus power supply unit with 13.8 VDC 6.2 A output, 230 V~ 50/60 Hz power supply

Product Status

3 - Active

Minimum order quantity


1 NR

Sheets, Manuals, Documentation


- [Multilanguage instructions sheet \(269 kb\)](#)
- [Feuille d'instructions \(202 kb\)](#)
- [Anwendungshinweise \(202 kb\)](#)




Drawings



Space view



Backside view



3D View

Technical data

- **Class group:** Low-voltage industrial components
- **Class:** AC/DC-power supply
- **Voltage type (supply voltage):** AC/DC
- **1st secondary output voltage AC:** 0 - 13 V
- **2nd secondary output voltage AC:** 0 - 13 V
- **Max. output current 1:** 5 A
- **Max. output current 2:** 1 A
- **Secondary voltage adjustable:** No
- **Short-circuit-proof:** Yes
- **Rated supply voltage AC 50 Hz:** 0 - 230 V
- **Rated supply voltage AC 60 Hz:** 0 - 230 V
- **Output voltage stabilized:** No
- **Power consumption:** 45 VA
- **Power output:** 85 W
- **Stabilized:** Yes
- **Type of electric connection:** Screw connection
- **Rail mounting possible:** No
- **Wall mounting possible:** No
- **Modular version:** No
- **Direct mounting possible:** No
- **Width:** 20.000,00 mm
- **Height:** 9.880,00 mm
- **Depth:** 5.070,00 mm
- **Suitable for safety functions:** Yes
- **SIL according to IEC 61508:** None
- **Performance level according to EN ISO 13849-1:** None
- **Degree of protection (IP):** IP00

Certifications

- 00. CE Marking - EU
- 37. Marking - Morocco
- 43. UKCA mark - Great Britain
- 99. WEEE Directive ([download](#))

Packaging



Code 8007352707283
Quantity 1 NR
Dim. 21.4x11.6x6 [cm]
Weight 806.6 [g]



Code 8007352707290
Quantity 10 NR
Dim. 30.5x25.5x22.5 [cm]
Weight 8,358 [g]

Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see [Conditions of Use](#).