



8000: 2P+E 10A P11 outlet

08140

Wiring devices / Traditional wiring devices / 8000 / Devices

2P+E 10A P11 outlet

2P+E 10 A 250 V~ SICURY socket outlet, Italian standard P11

Product Status

3 - Active

Minimum order quantity

50 NR



Technical data

- **Class group:** Domestic switching devices
- **Class:** Socket outlet
- **Model:** Italian type P11
- **Number of units:** 1
- **Number of modules (module system):** 1
- **Number of socket outlets switchable:** 0
- **Imprint/indication:** None
- **Connection type:** Screwed terminal
- **With hinged lid:** No
- **With enhanced contact protection:** Yes
- **Label space/information surface:** Yes
- **Colour:** White
- **RAL-number (similar):** 9001
- **Metallic colour:** No
- **Transparent:** No
- **Lockable:** No
- **Eject-mechanism:** No
- **Insulated mounting:** No
- **With function lighting:** No
- **Overvoltage protection:** No
- **Fault current protection:** No
- **Mounting method:** Flush-mounted
- **Type of fastening:** Snap mounting (engagement)
- **Material:** Plastic
- **Material quality:** Thermoplastic
- **Halogen free:** Yes
- **Surface protection:** Untreated
- **Surface finishing:** Matt
- **With loop through function:** No
- **With on/off switch:** No
- **Rotated central insert:** No
- **Nominal current:** 10 A
- **Nominal voltage:** 250 V
- **Frequency:** 50,00 - 60,00 HZ
- **Suitable for degree of protection (IP):** IP20
- **Impact strength:** Other
- **Device width:** 22,00 mm
- **Device height:** 50,10 mm
- **Device depth:** 32,50 mm

Certifications

- 00. CE Marking - EU
- 07. INGCER - Chile
- 37. Marking - Morocco
- 99. WEEE Directive ([download](#))

Packaging

			
Code 8007352014084	Code 8007352005112	Code 8007352361171	Code 8007352710405
Quantity 1 NR	Quantity 50 NR	Quantity 200 NR	Quantity 500 NR
Dim. 4.1x2.8x5.3 [cm]	Dim. 21.4x11.6x14.2 [cm]	Dim. 30.5x26x22 [cm]	Dim. 57.5x22.5x30 [cm]
Weight 25.5 [g]	Weight 1,356.47 [g]	Weight 5,765.88 [g]	Weight 14,414.5 [g]

Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see [Conditions of Use](#).