



8000: 2P+E 16A P17/11 outlet

08145

Wiring devices / Traditional wiring devices / 8000 / Devices

2P+E 16A P17/11 outlet

2P+E 16 A 250 V~ SICURY Bpresa socket outlet, Italian standard P17/11

Product Status

3 - Active

Minimum order quantity

50 NR



Technical data

- **Class group:** Domestic switching devices
- **Class:** Socket outlet
- **Model:** Italian type Bipasso
- **Number of units:** 1
- **Number of modules (module system):** 1
- **Number of socket outlets switchable:** 0
- **Imprint/indication:** None
- **Connection type:** Screwed terminal
- **With hinged lid:** No
- **With enhanced contact protection:** Yes
- **Label space/information surface:** Yes
- **Colour:** White
- **RAL-number (similar):** 9001
- **Metallic colour:** No
- **Transparent:** No
- **Lockable:** No
- **Eject-mechanism:** No
- **Insulated mounting:** No
- **With function lighting:** No
- **Over voltage protection:** No
- **Fault current protection:** No
- **Mounting method:** Flush-mounted
- **Type of fastening:** Snap mounting (engagement)
- **Material:** Plastic
- **Material quality:** Thermoplastic
- **Halogen free:** Yes
- **Surface protection:** Untreated
- **Surface finishing:** Matt
- **With loop through function:** No
- **With on/off switch:** No
- **Rotated central insert:** No
- **Nominal current:** 16 A
- **Nominal voltage:** 250 V
- **Frequency:** 50,00 - 60,00 HZ
- **Suitable for degree of protection (IP):** IP20
- **Impact strength:** Other
- **Device width:** 22,00 mm
- **Device height:** 50,10 mm
- **Device depth:** 32,50 mm

Certifications

- 00. CE Marking - EU
- 01. IMQ - Italy ([download](#))
- 07. INGCER - Chile
- 10. EAC Eurasian Customs Union
- 37. Marking - Morocco
- 99. WEEE Directive ([download](#))

Packaging



8 007352 014107

Code 8007352014107
Quantity 1 NR
Dim. 4.1x2.8x5.3 [cm]
Weight 27.2 [g]



8 007352 005082

Code 8007352005082
Quantity 50 NR
Dim. 21.4x11.6x14.2 [cm]
Weight 1,448 [g]



8 007352 263079

Code 8007352263079
Quantity 500 NR
Dim. 57.5x22.5x30 [cm]
Weight 15,024 [g]

Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see [Conditions of Use](#).