



## 8000: 2P+E 15A USA+SASO outlet

### 08195

Wiring devices / Traditional wiring devices / 8000 / Devices

### 2P+E 15A USA+SASO outlet

2P+E 15 A 127 V~ socket outlet, American and Saudi Arabian standards

### Product Status

3 - Active

### Minimum order quantity

50 NR



## Technical data

- **Class group:** Domestic switching devices
- **Class:** Socket outlet
- **Number of units:** 1
- **Number of modules (module system):** 1
- **Number of socket outlets switchable:** 0
- **Imprint/indication:** None
- **Connection type:** Screwed terminal
- **With hinged lid:** No
- **With enhanced contact protection:** No
- **Label space/information surface:** Yes
- **Colour:** White
- **RAL-number (similar):** 9001
- **Metallic colour:** No
- **Transparent:** No
- **Lockable:** No
- **Eject-mechanism:** No
- **Insulated mounting:** No
- **With function lighting:** No
- **Overvoltage protection:** No
- **Fault current protection:** No
- **Mounting method:** Flush-mounted
- **Type of fastening:** Snap mounting (engagement)
- **Material:** Plastic
- **Material quality:** Thermoplastic
- **Halogen free:** Yes
- **Surface protection:** Untreated
- **Surface finishing:** Matt
- **With loop through function:** No
- **With on/off switch:** No
- **Rotated central insert:** No
- **Nominal current:** 15 A
- **Nominal voltage:** 127 V
- **Frequency:** 50,00 - 60,00 HZ
- **Suitable for degree of protection (IP):** IP20
- **Impact strength:** Other
- **Device height:** 45,00 mm
- **Device depth:** 37,50 mm

## Certifications

- 00. CE Marking - EU
- 37. Marking - Morocco
- 96. Electrotechnical expert ([download](#))
- 99. WEEE Directive ([download](#))

## Packaging



8 007352 014282

**Code** 8007352014282  
**Quantity** 1 NR  
**Dim.** 4.1x2.8x5.3 [cm]  
**Weight** 29.6 [g]



8 007352 016576

**Code** 8007352016576  
**Quantity** 50 NR  
**Dim.** 21.4x11.6x14.2 [cm]  
**Weight** 1,561.13 [g]

## Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see [Conditions of Use](#).