



8000: 1P 10AX 1-way switch +key in OFF

08380.S

Wiring devices / Traditional wiring devices / 8000 / Devices

1P 10AX 1-way switch +key in OFF

1P 10 AX 250 V~ key-operated 1-way switch, key removable in 'O' (OFF) position only. Max 100 W for self-ballasted lamps (IEC 60669-1:2017)

Product Status

2 - Will be discontinued

Minimum order quantity

20 NR

Technical data

- **Class group:** Domestic switching devices
- **Class:** Installation switch
- **Wiring system:** Off switch 1-pole
- **Method of operation:** Key
- **Assembly arrangement:** Modular device for domestic switching devices
- **Number of modules (module system):** 1
- **Push button switch:** Yes
- **Number of rockers:** 0
- **Mounting method:** Flush-mounted
- **Type of fastening:** Engage (snap)
- **With mounting plate:** No
- **Material:** Plastic
- **Material quality:** Thermoplastic
- **Halogen free:** Yes
- **Surface protection:** Untreated
- **Surface finishing:** Matt
- **Colour:** Beige
- **RAL-number (similar):** 9001
- **Label space/information surface:** Yes
- **Illumination:** No
- **Function lighting:** Other
- **Type of lighting:** Other
- **Suitable for degree of protection (IP):** IP40
- **Nominal voltage:** 250 V
- **Rated current:** 10,00 A
- **Feedback-signal contact:** No
- **Connection type:** Screwed terminal
- **Washing machine switch:** No
- **Device height:** 45,00 mm
- **Device depth:** 43,00 mm
- **Built-in depth:** 33,50 mm



Certifications

- 00. CE Marking - EU
- 01. IMQ - Italy ([download](#))
- 10. EAC Eurasian Customs Union
- 14. TSE - Turkey
- 37. Marking - Morocco
- 43. UKCA mark - Great Britain
- 96. Electrotechnical expert ([download](#))
- 99. WEEE Directive ([download](#))

Packaging



Code	8007352142732	Code	8007352142749
Quantity	1 NR	Quantity	20 NR
Dim.	6x2.8x5.3 [cm]	Dim.	28.1x13.1x6 [cm]
Weight	43.73 [g]	Weight	948.73 [g]

Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see [Conditions of Use](#).