



8000: 2P+E 16A universal outlet red

08410.R

Wiring devices / Traditional wiring devices / 8000 / Devices

2P+E 16A universal outlet red

2P+E 16 A 250 V \sim SICURY socket outlet, universal, for 2P 2,5 A Europlugs, for 2P and 2P+E 10 A and 16 A Italian standard plugs, for 2P+E 16 A German standard plugs and for 2P 15 A 125 V \sim American standard plugs with non-polarized flat blades, red - 2 special modules. Earth connection is not realized with 16 A 2P+E 250 V \sim French standard plug



Product Status

2 - Will be discontinued

Minimum order quantity

20 NR

Technical data

Class group: Domestic switching devices

Class: Socket outlet

Model: Other

Number of units: 1

Number of modules (module system): 2

Number of socket outlets switchable: 0

Imprint/indication: None

Connection type: Screwed terminal

With hinged lid: No

• With enhanced contact protection: Yes
• Label space/information surface: Yes

Colour: Red

RAL-number (similar): 3001

Metallic colour: NoTransparent: NoLockable: No

Eject-mechanism: No
 Insulated mounting: No
 With function lighting: No
 With orientation lighting: No
 Over voltage protection: No

• Fault current protection: No

With miniature fuse: No

Mounting method: Flush-mounted

Type of fastening: Snap mounting (engagement)

Material: Plastic

Material quality: Thermoplastic

Halogen free: Yes

Surface protection: Untreated

Surface finishing: Matt

With loop through function: No

With on/off switch: No
 Rotated central insert: No
 Nominal current: 16 A
 Nominal voltage: 250 V
 Frequency: 50,00 - 60,00 HZ

Suitable for degree of protection (IP): IP20

Device height: 50,10 mm
Device depth: 42,00 mm

Certifications

00. CE Marking - EU

37. Marking - Morocco

99. WEEE Directive (download)

Packaging



 Code
 8007352153110

 Quantity
 1 NR

 Dim.
 5.1x4.3x5.3 [cm]

Dim. 5.1x4.3x5. **Weight** 58.47 [g]



Code 8007352153127 **Quantity** 20 NR

Dim. 26.9x11.6x9 [cm] **Weight** 1,239.2 [g]

Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see Conditions of Use.