



8000: TORCIA hand lamp 230V

08430

Wiring devices / Traditional wiring devices / 8000 / Devices

TORCIA hand lamp 230V

TORCIA, electronic hand lamp with high-efficiency LED, supply voltage 230 V~ 50-60 Hz, automatic emergency device, replaceable rechargeable Ni-MH battery, 2 hours of operating, ø 4 mm pins, 19 mm distance between centres + charging socket outlet - 2 special modules. Not suitable for flush-mounted charging socket outlets 08691... and 08591... It can be plugged for recharge also into any socket outlet for plugs with ø 4 mm pins, 19 mm distance between centres



Product Status

3 - Active

Minimum order quantity

10 NR

Sheets, Manuals, Documentation

- [Multilanguage instructions sheet \(484 kb\)](#)

Technical data

- **Class group:** Luminaires
- **Class:** Emergency luminaire
- **Mounting method:** Built-in
- **Monitoring equipment:** None
- **With remote switch connection:** No
- **Power supply system:** Peripheral (individual battery)
- **Battery quality:** NiMH
- **Lamp type:** LED not exchangeable
- **With light source:** Yes
- **Housing colour:** White
- **Voltage type:** AC
- **Nominal voltage:** 230,00 - 230,01 V
- **Degree of protection (IP):** IP40
- **Protection class:** II
- **Max. system power:** 1,00 W
- **Built-in height/depth:** 41,00 mm

Certifications

- 00. CE Marking - EU
- 37. Marking - Morocco
- 96. Electrotechnical expert ([download](#))
- 99. WEEE Directive ([download](#))

Packaging



Code 8007352090569
Quantity 1 NR
Dim. 6x5.4x5.3 [cm]
Weight 93.79 [g]

Code 8007352090576
Quantity 10 NR
Dim. 28.1x13.1x6 [cm]
Weight 1,013.87 [g]

Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see [Conditions of Use](#).