



## 8000: 2P+E 16A P30 outlet resin snapfix ivory

### 08614.A

Wiring devices / Traditional wiring devices / 8000 / Devices

#### 2P+E 16A P30 outlet resin snapfix ivory

2P+E 16 A 250 V~ SICURY socket outlet, Italian standard P30 (lateral and central earth contacts) - provided with mounting frame and resin cover plate for round mounting boxes, snap fixing, ivory



#### Product Status

2 - Will be discontinued

#### Minimum order quantity

10 NR

### Technical data

- **Class group:** Domestic switching devices
- **Class:** Socket outlet
- **Model:** Italian type P30
- **Number of units:** 1
- **Number of modules (module system):** 2
- **Number of socket outlets switchable:** 0
- **Imprint/indication:** None
- **Connection type:** Screwed terminal
- **With hinged lid:** No
- **With enhanced contact protection:** Yes
- **Label space/information surface:** Yes
- **Colour:** White
- **RAL-number (similar):** 9001
- **Metallic colour:** No
- **Transparent:** No
- **Lockable:** No
- **Eject-mechanism:** No
- **Insulated mounting:** No
- **With function lighting:** No
- **Over voltage protection:** No
- **Fault current protection:** No
- **Mounting method:** Flush-mounted
- **Material:** Plastic
- **Material quality:** Thermoplastic
- **Halogen free:** Yes
- **Surface protection:** Untreated
- **Surface finishing:** Matt
- **With loop through function:** No
- **With on/off switch:** No
- **Rotated central insert:** No
- **Nominal current:** 16 A
- **Nominal voltage:** 250 V
- **Frequency:** 50,00 - 60,00 HZ
- **Suitable for degree of protection (IP):** IP20
- **Impact strength:** Other
- **Device height:** 45,00 mm

# Certifications

- 00. CE Marking - EU
- 01. IMQ - Italy ([download](#))
- 37. Marking - Morocco
- 99. WEEE Directive ([download](#))

# Packaging



<b>Code</b>	8007352042032	<b>Code</b>	8007352017719
<b>Quantity</b>	1 NR	<b>Quantity</b>	10 NR
<b>Dim.</b>	8x8x4.5 [cm]	<b>Dim.</b>	28.1x13.1x11.3 [cm]
<b>Weight</b>	75.87 [g]	<b>Weight</b>	871.53 [g]

# Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see [Conditions of Use](#).