



8000: 2P+E 16A P30 outlet alum.snapfix bronze

08614.BR

Wiring devices / Traditional wiring devices / 8000 / Devices

2P+E 16A P30 outlet alum.snapfix bronze

2P+E 16 A 250 V~ SICURY socket outlet, Italian standard P30 (lateral and central earth contacts) - provided with mounting frame and anodized aluminium cover plate for round mounting boxes, snap fixing, bronze



Product Status

2 - Will be discontinued

Minimum order quantity

10 NR

Technical data

- **Class group:** Domestic switching devices
- **Class:** Socket outlet
- **Model:** Italian type P30
- **Number of units:** 1
- **Number of modules (module system):** 2
- **Number of socket outlets switchable:** 0
- **Imprint/indication:** None
- **Connection type:** Screwed terminal
- **With hinged lid:** No
- **With enhanced contact protection:** Yes
- **Label space/information surface:** Yes
- **Colour:** White
- **RAL-number (similar):** 9001
- **Metallic colour:** No
- **Transparent:** No
- **Lockable:** No
- **Eject-mechanism:** No
- **Insulated mounting:** No
- **With function lighting:** No
- **Over voltage protection:** No
- **Fault current protection:** No
- **Mounting method:** Flush-mounted
- **Material:** Plastic
- **Material quality:** Thermoplastic
- **Halogen free:** Yes
- **Surface protection:** Untreated
- **Surface finishing:** Matt
- **With loop through function:** No
- **With on/off switch:** No
- **Rotated central insert:** No
- **Nominal current:** 16 A
- **Nominal voltage:** 250 V
- **Frequency:** 50,00 - 60,00 HZ
- **Suitable for degree of protection (IP):** IP20
- **Impact strength:** Other
- **Device width:** 79,50 mm
- **Device height:** 45,00 mm

Certifications

- 00. CE Marking - EU
- 01. IMQ - Italy ([download](#))
- 37. Marking - Morocco
- 99. WEEE Directive ([download](#))

Packaging



Code 8007352042049
Quantity 1 NR
Dim. 8x8x4.5 [cm]
Weight 72.47 [g]

Code 8007352017665
Quantity 10 NR
Dim. 26.9x11.6x9 [cm]
Weight 804.73 [g]

Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see [Conditions of Use](#).