



NEVE UP: Button 1M +diffuser PLS symb.carbon matt

09026.PLS.CM

Wiring devices / Traditional wiring devices / NEVE UP / Buttons

Button 1M +diffuser PLS symb.carbon matt

1-module interchangeable button, lightTable Please Clean symbol with speaker, carbon matt

Product Status

3 - Active

Minimum order quantity

50 NR



You may also be interested in




09026.DND.CM - Button 1M 09097 - Pushbutton +2 Hotel 09470.CM - Dial thermostat 100-240V 2M carbon m



09290.CM - Shaver supply unit 230V carbon matt



09463.CM - Vertical badge switch 2M carbon matt




09465.CM - Vertical pocket badge switch carbon matt



09257.CM - 2P+E13ASICURY 09052.CM - 1P NO 10A cord-operated push carbon matt



09181.CM - IR relay-switch 230V carbon matt



Space view





Backside view



3D View

Drawings




Technical data

- **Class group:** Domestic switching devices
- **Class:** Control element/cover plate for domestic switching devices
- **Model:** One-part rocker
- **Utilization:** Switch/push button
- **Suitable for touch sensor connector for bus system:** No
- **Type of fastening:** Clamp mounting
- **Monitoring window/light outlet:** Yes
- **Material:** Plastic
- **Material quality:** Thermoplastic
- **Surface protection:** Lacquered
- **Surface finishing:** Matt
- **Colour:** Anthracite
- **RAL-number (similar):** 7016
- **With exchangeable lens/symbol:** Yes
- **Depth:** 750,00 mm


Certifications

- 00. CE Marking - EU
- 29. QCERT - Colombia ([download](#))
- 29. QCERT - Colombia
- 43. UKCA mark - Great Britain

Packaging



Code 8007352663596
Quantity 1 NR
Dim. 2.2x4.4x1.1 [cm]
Weight 6.349 [g]



Code 8007352663602
Quantity 5 NR
Dim. 5.1x2.8x5.3 [cm]
Weight 24.14 [g]



Code 8007352663619
Quantity 50 NR
Dim. 14.4x11.6x6 [cm]
Weight 282.49 [g]



Code 8007352668751
Quantity 600 NR
Dim. 36.5x33x13.5 [cm]
Weight 3,809.88 [g]

Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see [Conditions of Use](#).