



## NEVE UP: 2P+E 16A P30 outlet carbon matt

**09209.CM**

Wiring devices / Traditional wiring devices / NEVE UP / Devices

### 2P+E 16A P30 outlet carbon matt

2P+T 16 A 250 V~ SICURY socket outlet, Italian standard type P30 (side and central earth contacts), carbon matt - 2 modules

### Product Status

3 - Active

### Minimum order quantity

20 NR




You may also be interested in




[09210.CM - 2P+E 16A universal outlet carbon matt](#)


## Drawings



Space view



Backside view



3D View

## Technical data

- **Class group:** Domestic switching devices
- **Class:** Socket outlet
- **Model:** Italian type P30
- **Number of modules (module system):** 2
- **With hinged lid:** No
- **Label space/information surface:** Yes
- **Colour:** Anthracite
- **RAL-number (similar):** 7016
- **Metallic colour:** No
- **Transparent:** No
- **Lockable:** No
- **Eject-mechanism:** No
- **Insulated mounting:** No
- **Mounting method:** Flush-mounted
- **Material:** Plastic
- **Material quality:** Thermoplastic
- **Surface protection:** Lacquered
- **Surface finishing:** Matt
- **Anti-bacterial treatment:** No
- **With loop through function:** No
- **With on/off switch:** No
- **Rotated central insert:** No
- **Nominal current:** 16 A
- **Nominal voltage:** 250 V
- **Frequency:** 50,00 - 60,00 HZ
- **Device width:** 44,80 mm
- **Device height:** 47,00 mm
- **Device depth:** 38,80 mm

## Certifications

- 00. CE Marking - EU
- 10. EAC Eurasian Customs Union
- 13. SNI - Indonesia
- 37. Marking - Morocco
- 99. WEEE Directive ([download](#))

## Packaging



**Code** 8007352665613  
**Quantity** 1 NR  
**Dim.** 5.1x4.3x5.3 [cm]  
**Weight** 44.8 [g]



**Code** 8007352665620  
**Quantity** 20 NR  
**Dim.** 26.9x11.6x9 [cm]  
**Weight** 991.47 [g]



**Code** 8007352665637  
**Quantity** 240 NR  
**Dim.** 38x28.5x35.5 [cm]  
**Weight** 12,398.67 [g]

## Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see [Conditions of Use](#).