



## NEVE UP: TORCIA hand lamp 230V white

**09395**

Wiring devices / Traditional wiring devices / NEVE UP / Devices

### TORCIA hand lamp 230V white

TORCIA, portable electronic hand lamp with high-efficiency LEDs 230 V~ 50-60 Hz, automatic emergency device, replaceable and rechargeable Ni-MH battery, 2 hours' autonomy,  $\varnothing$  4 mm pin, distance between centres 19 mm + charging socket, white - 2 modules

### Product Status

3 - Active


### Minimum order quantity

10 NR


### Sheets, Manuals, Documentation

- [Multilanguage instructions sheet \(673 kb\)](#)


### Drawings



Space view



Backside view



3D View




## Technical data

- **Class group:** Luminaires
- **Class:** Emergency luminaire
- **Mounting method:** Built-in
- **Monitoring equipment:** None
- **With remote switch connection:** No
- **Power supply system:** Peripheral (individual battery)
- **Battery quality:** NiMH
- **Lamp type:** LED not exchangeable
- **With light source:** Yes
- **Housing material:** Plastic
- **Housing colour:** White
- **Material cover:** Without cover
- **Voltage type:** AC
- **Nominal voltage:** 230,00 - 230,01 V
- **Max. system power:** 1,00 W
- **Width:** 44,80 mm
- **Height/depth:** 58,00 mm
- **Length:** 47,00 mm
- **Built-in width:** 44,80 mm
- **Built-in height/depth:** 41,30 mm
- **Built-in length:** 47,00 mm
- **Connection type:** Other

## Certifications

- 00. CE Marking - EU
- 10. EAC Eurasian Customs Union
- 37. Marking - Morocco
- 43. UKCA mark - Great Britain
- 99. WEEE Directive ([download](#))

## Packaging



**Code** 8007352664579  
**Quantity** 1 NR  
**Dim.** 6x5.4x5.3 [cm]  
**Weight** 83.4 [g]



**Code** 8007352664586  
**Quantity** 10 NR  
**Dim.** 28.1x13.1x6 [cm]  
**Weight** 910.8 [g]



**Code** 8007352667198  
**Quantity** 50 NR  
**Dim.** 37.5x30x13.5 [cm]  
**Weight** 4,914 [g]

## Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see [Conditions of Use](#).