



LINEA Classica: Dimmer 120V 30-500W/30-300VA

10337

Wiring devices / Traditional wiring devices / LINEA Classica / Devices

Dimmer 120V 30-500W/30-300VA

Dimmer, 120 V~ 50-60 Hz, for: 30-500 W incandescent lamps, 30-300 VA ferromagnetic transformers, without radio interference suppression filter, control and regulation by rotary potentiometer, visible in darkness

Product Status

2 - Will be discontinued

Minimum order quantity

20 NR

Sheets, Manuals, Documentation

- [Multilanguage instructions sheet \(213 kb\)](#)



Technical data

- **Class group:** Domestic switching devices
- **Class:** Dimmer
- **Method of operation:** Turn button
- **Mounting method:** Flush-mounted
- **Type of fastening:** Snapper mounting
- **Material:** Plastic
- **Material quality:** Thermoplastic
- **Surface protection:** Untreated
- **Surface finishing:** Matt
- **Colour:** White
- **RAL-number (similar):** 9001
- **Transparent:** No
- **Nominal voltage:** 120,00 - 120,01 V
- **Device width:** 22,00 mm
- **Device height:** 36,00 mm
- **Device depth:** 48,00 mm

Certifications

- 00. CE Marking - EU
- 10. EAC Eurasian Customs Union
- 19. NOM - Mexico
- 37. Marking - Morocco
- 43. UKCA mark - Great Britain
- 99. WEEE Directive ([download](#))

Packaging



Code 8007352045989
Quantity 1 NR
Dim. 6x2.8x5.3 [cm]
Weight 38.2 [g]

Code 8007352046696
Quantity 20 NR
Dim. 28.1x13.1x6 [cm]
Weight 841.47 [g]

Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see [Conditions of Use](#).