



PLANA: 1P NC 10A push button white

14010

Wiring devices / Traditional wiring devices / PLANA / Devices

1P NC 10A push button white

1P NC 10 A 250 V~ push button, lightable, replaceable button, white

Product Status


3 - Active

Minimum order quantity

10 NR




Drawings



Space view



Backside view



3D View

Gallery



Technical data

- **Class group:** Domestic switching devices
- **Class:** Push button
- **Assembly arrangement:** Modular device for domestic switching devices
- **Model:** Single push button
- **Method of operation:** Push button
- **Number of rockers:** 1
- **Number of modules (module system):** 100
- **Number of poles:** 1
- **Nominal voltage:** 250 V
- **Rated current:** 10,00 A
- **With lighting:** Yes
- **Feedback-signal contact:** No
- **Mounting method:** Flush-mounted
- **Type of fastening:** Engage (snap)
- **Material:** Plastic
- **Material quality:** Thermoplastic
- **Halogen free:** Yes
- **Surface protection:** Untreated
- **Surface finishing:** Glossy
- **Colour:** White
- **RAL-number (similar):** 9003
- **Transparent:** No
- **Label space/information surface:** Yes
- **Suitable for degree of protection (IP):** IP40
- **Device width:** 22,30 mm
- **Device height:** 49,00 mm
- **Device depth:** 38,70 mm

Certifications

- 00. CE Marking - EU
- 01. IMQ - Italy ([download](#))
- 10. EAC Eurasian Customs Union
- 14. TSE - Turkey
- 15. CCC - China ([download](#))
- 19. NOM - Mexico
- 20. IQC - Argentina
- 28. NSW - Australia ([download](#))
- 29. QCERT - Colombia
- 31. TISI - Thailand
- 37. Marking - Morocco
- 43. UKCA mark - Great Britain
- 96. Electrotechnical expert ([download](#))
- 99. WEEE Directive ([download](#))

Packaging



Code 8007352117259
Quantity 1 NR
Dim. 4.1x2.8x5.3 [cm]
Weight 27.7 [g]



Code 8007352263680
Quantity 10 NR
Dim. 14.4x9x6 [cm]
Weight 317.07 [g]



Code 8007352634169
Quantity 160 NR
Dim. 37.5x30x13.5 [cm]
Weight 5,073.6 [g]

Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see [Conditions of Use](#).