



PLANA: 2P+E 16A USA+EU SICURY outlet Silver

14248.SL

Wiring devices / Traditional wiring devices / PLANA / Devices

2P+E 16A USA+EU SICURY outlet Silver

2P+E 16 A 250 V~ SICURY socket outlet, polarized Euro-American standard, Silver - 2 modules


Product Status

3 - Active


Minimum order quantity

20 NR


Drawings




Space view



Backside view



3D View



Technical data

- **Class group:** Domestic switching devices
- **Class:** Socket outlet
- **Model:** Other
- **Number of units:** 1
- **Number of modules (module system):** 2
- **Number of socket outlets switchable:** 0
- **Imprint/indication:** None
- **Connection type:** Screwed terminal
- **With hinged lid:** No
- **With enhanced contact protection:** Yes
- **Label space/information surface:** Yes
- **Colour:** Silver
- **RAL-number (similar):** 9006
- **Metallic colour:** No
- **Transparent:** No
- **Lockable:** No
- **Eject-mechanism:** No
- **Insulated mounting:** No
- **With function lighting:** No
- **Over voltage protection:** No
- **Fault current protection:** No
- **Mounting method:** Flush-mounted
- **Material:** Plastic
- **Material quality:** Thermoplastic
- **Halogen free:** Yes
- **Surface protection:** Lacquered
- **Surface finishing:** Glossy
- **With loop through function:** No
- **With on/off switch:** No
- **Rotated central insert:** No
- **Nominal current:** 16 A
- **Nominal voltage:** 250 V
- **Frequency:** 50,00 - 60,00 HZ
- **Suitable for degree of protection (IP):** IP20
- **Impact strength:** Other
- **Device width:** 44,80 mm
- **Device height:** 49,00 mm
- **Device depth:** 36,00 mm

Certifications

- 10. EAC Eurasian Customs Union
- 29. QCERT - Colombia ([download](#))
- 37. Marking - Morocco

Packaging



Code 8007352467552
Quantity 1 NR
Dim. 5.1x4.3x5.3 [cm]
Weight 44.9 [g]



Code 8007352467569
Quantity 20 NR
Dim. 26.9x11.6x9 [cm]
Weight 979.2 [g]

Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see [Conditions of Use](#).