



PLANA: 3-sound-sequence chime 12V Silver

14380.SL

Wiring devices / Traditional wiring devices / PLANA / Devices

3-sound-sequence chime 12V Silver

3-sound-sequence electronic chime (three-tone, two-tone, buzzer), adjustable volume, supply voltage 12 V~ 50-60 Hz or 12 Vdc (SELV), Silver - 2 modules

Product Status

3 - Active

Minimum order quantity


5 NR

Sheets, Manuals, Documentation


- [Sound-sequence \(412 kb\)](#)
- [Multilanguage instructions sheet \(584 kb\)](#)




Drawings



Space view



Backside view



3D View

Technical data

- **Class group:** Optical and acoustic signalling equipment
- **Class:** Bell
- **Housing colour:** Grey
- **Housing material:** Plastic
- **Loudness:** 70 dB
- **Nominal voltage:** 12,00 - 12,01 V
- **Degree of protection (IP):** IP40
- **Type of current:** AC/DC
- **Built-in battery:** No
- **Mounting method:** Flush-mounted
- **Width in number of modular spacings:** 2
- **Wireless:** No

Certifications

- 00. CE Marking - EU
- 37. Marking - Morocco
- 43. UKCA mark - Great Britain
- 96. Electrotechnical expert ([download](#))
- 99. WEEE Directive ([download](#))

Packaging



Code 8007352319677
Quantity 1 NR
Dim. 6x5.4x5.3 [cm]
Weight 82.9 [g]

Code 8007352319684
Quantity 5 NR
Dim. 17.2x13.1x6 [cm]
Weight 476.93 [g]

Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see [Conditions of Use](#).