



IDEA: 1P NO 10A push key symbol grey

16080.P

Wiring devices / Traditional wiring devices / IDEA / Devices

1P NO 10A push key symbol grey

1P NO 10 A 250 V~ push button, key symbol, grey

Product Status


3 - Active

Minimum order quantity


20 NR




Drawings



Space view



Backside view



3D View

Technical data

- **Class group:** Domestic switching devices
- **Class:** Push button
- **Assembly arrangement:** Modular device for domestic switching devices
- **Model:** Single push button
- **Method of operation:** Push button
- **Number of rockers:** 0
- **Number of modules (module system):** 100
- **Number of poles:** 1
- **Nominal voltage:** 250 V
- **Rated current:** 10,00 A
- **With lighting:** No
- **Feedback-signal contact:** No
- **Mounting method:** Flush-mounted
- **Type of fastening:** Engage (snap)
- **Material:** Plastic
- **Material quality:** Thermoplastic
- **Halogen free:** Yes
- **Surface protection:** Untreated
- **Surface finishing:** Matt
- **Colour:** Grey
- **RAL-number (similar):** 7015
- **Transparent:** No
- **Label space/information surface:** Yes
- **Suitable for degree of protection (IP):** IP40
- **Device width:** 24,80 mm
- **Device height:** 50,10 mm
- **Device depth:** 36,10 mm

Certifications

- 00. CE Marking - EU
- 01. IMQ - Italy
- 10. EAC Eurasian Customs Union
- 14. TSE - Turkey
- 15. CCC - China ([download](#))
- 19. NOM - Mexico
- 20. IQC - Argentina
- 28. NSW - Australia ([download](#))
- 37. Marking - Morocco
- 43. UKCA mark - Great Britain
- 96. Electrotechnical expert ([download](#))
- 99. WEEE Directive ([download](#))

Packaging



8 007352 005549

Code 8007352005549
Quantity 1 NR
Dim. 4.1x2.8x5.3 [cm]
Weight 24.4 [g]



8 007352 000629

Code 8007352000629
Quantity 20 NR
Dim. 21.4x11.6x6 [cm]
Weight 547.53 [g]



8 007352 641990

Code 8007352641990
Quantity 200 NR
Dim. 30.5x25.5x22.5 [cm]
Weight 5,800 [g]

Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see [Conditions of Use](#).