



IDEA: 1P 10AX 2-way switch grey

16140

Wiring devices / Traditional wiring devices / IDEA / Devices

1P 10AX 2-way switch grey

1P 10 AX 250 V~ 2-way switch (3 terminals) with directional arrows and central OFF position, grey. Max 100 W for self-ballasted lamps (IEC 60669-1:2017)


Product Status

3 - Active


Minimum order quantity

10 NR


Drawings



Space view



Backside view



3D View



Technical data

- **Class group:** Domestic switching devices
- **Class:** Push button
- **Assembly arrangement:** Modular device for domestic switching devices
- **Model:** Other
- **Method of operation:** Rocker
- **Number of rockers:** 1
- **Number of modules (module system):** 100
- **Number of poles:** 1
- **Nominal voltage:** 250 V
- **Rated current:** 10,00 A
- **With lighting:** No
- **Feedback-signal contact:** No
- **Mounting method:** Flush-mounted
- **Type of fastening:** Engage (snap)
- **Material:** Plastic
- **Material quality:** Thermoplastic
- **Halogen free:** Yes
- **Surface protection:** Untreated
- **Surface finishing:** Matt
- **Colour:** Grey
- **RAL-number (similar):** 7015
- **Transparent:** No
- **Label space/information surface:** Yes
- **Suitable for degree of protection (IP):** IP40
- **Device width:** 24,80 mm
- **Device height:** 50,10 mm
- **Device depth:** 43,60 mm

Certifications

- 00. CE Marking - EU
- 01. IMQ - Italy
- 10. EAC Eurasian Customs Union
- 14. TSE - Turkey
- 15. CCC - China ([download](#))
- 20. IQC - Argentina
- 28. NSW - Australia ([download](#))
- 37. Marking - Morocco
- 43. UKCA mark - Great Britain
- 96. Electrotechnical expert ([download](#))
- 99. WEEE Directive ([download](#))

Packaging



Code 8007352002494
Quantity 1 NR
Dim. 5.1x2.8x5.3 [cm]
Weight 33.6 [g]



Code 8007352264083
Quantity 10 NR
Dim. 14.4x11.6x6 [cm]
Weight 379.13 [g]



Code 8007352643284
Quantity 120 NR
Dim. 36.5x33x13.5 [cm]
Weight 5,328 [g]

Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see [Conditions of Use](#).