IDEA: 2P+E 16A P30 outlet orange

16209.A

Wiring devices / Traditional wiring devices / IDEA / Devices

2P+E 16A P30 outlet orange

2P+E 16 A 250 V~ SICURY socket outlet, Italian standard P30 (lateral and central earth contacts), orange - 2 modules

Product Status

2 - Will be discontinued

Minimum order quantity

20 NR

Drawings



Space view



Backside view



3D View

Technical data

- **Class group**: Domestic switching devices
- **Class**: Socket outlet
- **Model**: Italian type P30
- **Number of modules (module system)**: 2
- **Number of socket outlets switchable**: 0
- **Imprint/indication**: None
- **Connection type**: Screwed terminal
- **With hinged lid**: No
- **With enhanced contact protection**: Yes
- **Label space/information surface**: Yes
- **Colour**: Orange
- **RAL-number (similar)**: 9001
- **Metallic colour**: No
- **Transparent**: No
- **Lockable**: No
- **Eject-mechanism**: No
- **Insulated mounting**: No
- **With function lighting**: No
- **With orientation lighting**: No
- **Over voltage protection**: No
- **Fault current protection**: No
- **With miniature fuse**: No
- **Mounting method**: Flush-mounted
- **Type of fastening**: Snap mounting (engagement)
- **Material**: Plastic
- **Material quality**: Thermoplastic
- **Halogen free**: Yes
- **Surface protection**: Untreated
- **Surface finishing**: Matt
- **With loop through function**: No
- **With on/off switch**: No
- **Rotated central insert**: No
- **Nominal current**: 16 A
- **Nominal voltage**: 250 V
- **Frequency**: 50,00 - 60,00 HZ
- **Suitable for degree of protection (IP)**: IP20
- **Impact strength**: Other
- **Device width**: 49,80 mm
- **Device height**: 50,10 mm
- **Device depth**: 38,80 mm

Certifications

- 00. CE Marking - EU
- 37. Marking - Morocco

Packaging

8 007352 100671

Code	8007352100671
Quantity	1 NR
Dim.	5.1x4.3x5.3 [cm]
Weight	48.6 [g]

8 007352 100688

Code	8007352100688
Quantity	20 NR
Dim.	26.9x11.6x9 [cm]
Weight	1,050.33 [g]

Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported.Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed.For the terms of use of the information on the product info sheet see Conditions of Use.