



IDEA: 2P+E 10A Australian SICURY-outlet white

16261.B

Wiring devices / Traditional wiring devices / IDEA / Devices

2P+E 10A Australian SICURY-outlet white

2P+E 10 A 250 V~ SICURY socket outlet, Australian standard, white - 2 modules


Product Status

3 - Active


Minimum order quantity

20 NR


Drawings



Space view



Backside view



3D View




Technical data

- **Class group:** Domestic switching devices
- **Class:** Socket outlet
- **Model:** Australian standard AS/NZS 3112 (type I)
- **Number of units:** 1
- **Number of modules (module system):** 2
- **Number of socket outlets switchable:** 0
- **Imprint/indication:** None
- **Connection type:** Screwed terminal
- **With hinged lid:** No
- **With enhanced contact protection:** Yes
- **Label space/information surface:** Yes
- **Colour:** White
- **RAL-number (similar):** 9001
- **Metallic colour:** No
- **Transparent:** No
- **Lockable:** No
- **Eject-mechanism:** No
- **Insulated mounting:** No
- **With function lighting:** No
- **Over voltage protection:** No
- **Fault current protection:** No
- **Mounting method:** Flush-mounted
- **Material:** Plastic
- **Material quality:** Thermoplastic
- **Halogen free:** Yes
- **Surface protection:** Untreated
- **Surface finishing:** Matt
- **With loop through function:** No
- **With on/off switch:** No
- **Rotated central insert:** No
- **Nominal current:** 10 A
- **Nominal voltage:** 250 V
- **Frequency:** 50,00 - 60,00 HZ
- **Suitable for degree of protection (IP):** IP20
- **Impact strength:** Other
- **Device width:** 49,80 mm
- **Device height:** 50,10 mm
- **Device depth:** 38,70 mm

Certifications

- 00. CE Marking - EU
- 28. NSW - Australia ([download](#))
- 37. Marking - Morocco
- 99. WEEE Directive ([download](#))

Packaging



Code 8007352293441
Quantity 1 NR
Dim. 5.1x4.3x5.3 [cm]
Weight 48.2 [g]



Code 8007352293458
Quantity 20 NR
Dim. 26.9x11.6x9 [cm]
Weight 1,039.67 [g]

Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see [Conditions of Use](#).