



IDEA: 1P 16AX 2-way switch lums grey

17003.L

Wiring devices / Traditional wiring devices / IDEA / Devices

1P 16AX 2-way switch lums grey

1P 16 AX 250 V~ 2-way switch, luminous, for signalling unit, grey - reduced module. Provided without signalling unit. Max 200 W for self-ballasted lamps (IEC 60669-1:2017)

Product Status

3 - Active

Minimum order quantity

20 NR



Technical data

- **Class group:** Domestic switching devices
- **Class:** Installation switch
- **Wiring system:** Two-way switch
- **Method of operation:** Rocker/button
- **Assembly arrangement:** Modular device for domestic switching devices
- **Number of modules (module system):** 1
- **Push button switch:** Yes
- **Number of rockers:** 1
- **Mounting method:** Flush-mounted
- **Type of fastening:** Engage (snap)
- **With mounting plate:** No
- **Material:** Plastic
- **Material quality:** Thermoplastic
- **Halogen free:** Yes
- **Surface protection:** Untreated
- **Surface finishing:** Matt
- **Colour:** Grey
- **RAL-number (similar):** 7015
- **Label space/information surface:** Yes
- **Illumination:** Optional
- **Function lighting:** Control and orientation
- **Type of lighting:** LED exchangeable
- **Suitable for degree of protection (IP):** IP40
- **Nominal voltage:** 250 V
- **Rated current:** 16,00 A
- **Feedback-signal contact:** No
- **Connection type:** Screwed terminal
- **Washing machine switch:** No
- **Device width:** 21,80 mm
- **Device height:** 50,10 mm
- **Device depth:** 32,50 mm
- **Built-in depth:** 23,30 mm

Certifications

- 00. CE Marking - EU
- 01. IMQ - Italy
- 10. EAC Eurasian Customs Union
- 14. TSE - Turkey
- 19. NOM - Mexico
- 28. NSW - Australia ([download](#))
- 37. Marking - Morocco
- 43. UKCA mark - Great Britain
- 96. Electrotechnical expert ([download](#))
- 99. WEEE Directive ([download](#))

Packaging



Code 8007352078406
Quantity 1 NR
Dim. 4.1x2.8x5.3 [cm]
Weight 27.13 [g]

Code 8007352078413
Quantity 20 NR
Dim. 21.4x11.6x6 [cm]
Weight 601.8 [g]

Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see [Conditions of Use](#).