



ARKÉ: 1P NC 10A push button mechanism

19010.0

Wiring devices / Traditional wiring devices / ARKÉ / Devices

1P NC 10A push button mechanism

1P NC 10 A 250 V~ push button mechanism, lightable, to complete with 1, 2 or 3-module button

Product Status

3 - Active

Minimum order quantity


10 NR

Video


- [Arké lives in your time](#)



Drawings



Space view



3D View

Gallery



Technical data

- **Class group:** Domestic switching devices
- **Class:** Push button
- **Assembly arrangement:** Modular device for domestic switching devices
- **Model:** Single push button
- **Method of operation:** Push button
- **Number of rockers:** 1
- **Number of modules (module system):** 100
- **Number of poles:** 1
- **Nominal voltage:** 250 V
- **Rated current:** 10,00 A
- **With lighting:** Yes
- **Feedback-signal contact:** No
- **Mounting method:** Flush-mounted
- **Type of fastening:** Engage (snap)
- **Material:** Plastic
- **Material quality:** Thermoplastic
- **Halogen free:** Yes
- **Surface protection:** Untreated
- **Surface finishing:** Matt
- **Colour:** Blue
- **RAL-number (similar):** 7015
- **Transparent:** No
- **Label space/information surface:** Yes
- **Suitable for degree of protection (IP):** IP40
- **Device width:** 22,30 mm
- **Device height:** 49,00 mm
- **Device depth:** 36,80 mm

Certifications

- 00. CE Marking - EU
- 01. IMQ - Italy ([download](#))
- 10. EAC Eurasian Customs Union
- 14. TSE - Turkey
- 19. NOM - Mexico
- 29. QCERT - Colombia
- 36. ISI - India
- 37. Marking - Morocco
- 43. UKCA mark - Great Britain
- 96. Electrotechnical expert ([download](#))
- 99. WEEE Directive ([download](#))

Packaging



8 007352 413115

Code 8007352413115
Quantity 1 NR
Dim. 4.1x2.8x5.3 [cm]
Weight 22.7 [g]



8 007352 413122

Code 8007352413122
Quantity 10 NR
Dim. 14.4x9x6 [cm]
Weight 265 [g]

Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see [Conditions of Use](#).