



## ARKÉ: Two independent NO+NC 10A pushes Metal

### 19058.M

Wiring devices / Traditional wiring devices / ARKÉ / Devices

### Two independent NO+NC 10A pushes Metal

Two independent push buttons, 1P NO + 1P NC 10 A 250 V~, ON and OFF symbols, Metal

### Product Status

3 - Active

### Minimum order quantity

20 NR


### Video

- [Arké lives in your time](#)


## Drawings



Space view



Backside view



3D View




## Technical data

- **Class group:** Domestic switching devices
- **Class:** Push button
- **Assembly arrangement:** Modular device for domestic switching devices
- **Model:** Other
- **Method of operation:** Push button
- **Number of rockers:** 2
- **Number of modules (module system):** 100
- **Number of poles:** 1
- **Nominal voltage:** 250 V
- **Rated current:** 10,00 A
- **With lighting:** No
- **Feedback-signal contact:** No
- **Mounting method:** Flush-mounted
- **Type of fastening:** Engage (snap)
- **Material:** Plastic
- **Material quality:** Thermoplastic
- **Halogen free:** Yes
- **Surface protection:** Lacquered
- **Surface finishing:** Matt
- **Colour:** Aluminium
- **RAL-number (similar):** 9007
- **Transparent:** No
- **Label space/information surface:** Yes
- **Suitable for degree of protection (IP):** IP40
- **Device width:** 22,30 mm
- **Device height:** 49,00 mm
- **Device depth:** 39,20 mm

## Certifications

- 00. CE Marking - EU
- 01. IMQ - Italy ([download](#))
- 10. EAC Eurasian Customs Union
- 14. TSE - Turkey
- 19. NOM - Mexico
- 29. QCERT - Colombia
- 31. TISI - Thailand
- 36. ISI - India
- 37. Marking - Morocco
- 43. UKCA mark - Great Britain
- 96. Electrotechnical expert ([download](#))
- 99. WEEE Directive ([download](#))

## Packaging



8 007352 599864

**Code** 8007352599864  
**Quantity** 1 NR  
**Dim.** 4.1x2.8x5.3 [cm]  
**Weight** 32.9 [g]



8 007352 599871

**Code** 8007352599871  
**Quantity** 20 NR  
**Dim.** 21.4x11.6x6 [cm]  
**Weight** 715 [g]

## Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see [Conditions of Use](#).