



ARKÉ: 1P NO 10A push+indicator unit Metal

19068.M

Wiring devices / Traditional wiring devices / ARKÉ / Devices

1P NO 10A push+indicator unit Metal

1P NO 10 A 250 V~ push button + indicator unit for signalling unit, neutral diffuser, Metal. Provided without signalling unit

Product Status

3 - Active

Minimum order quantity


20 NR

Video


- [Arké lives in your time](#)




Drawings



Space view



Backside view



3D View

Technical data

- **Class group:** Domestic switching devices
- **Class:** Push button
- **Assembly arrangement:** Modular device for domestic switching devices
- **Model:** Single push button
- **Method of operation:** Push button
- **Number of rockers:** 1
- **Number of modules (module system):** 100
- **Number of poles:** 1
- **Nominal voltage:** 250 V
- **Rated current:** 10,00 A
- **With lighting:** Yes
- **Feedback-signal contact:** No
- **Mounting method:** Flush-mounted
- **Type of fastening:** Engage (snap)
- **Material:** Plastic
- **Material quality:** Thermoplastic
- **Halogen free:** Yes
- **Surface protection:** Lacquered
- **Surface finishing:** Matt
- **Colour:** Aluminium
- **RAL-number (similar):** 9007
- **Transparent:** No
- **Label space/information surface:** Yes
- **Suitable for degree of protection (IP):** IP40
- **Device width:** 22,30 mm
- **Device height:** 49,00 mm
- **Device depth:** 38,70 mm

Certifications

- 00. CE Marking - EU
- 01. IMQ - Italy ([download](#))
- 10. EAC Eurasian Customs Union
- 14. TSE - Turkey
- 29. QCERT - Colombia
- 31. TISI - Thailand
- 36. ISI - India
- 37. Marking - Morocco
- 43. UKCA mark - Great Britain
- 96. Electrotechnical expert ([download](#))
- 99. WEEE Directive ([download](#))

Packaging



8 007352 596139

Code 8007352596139
Quantity 1 NR
Dim. 4.1x2.8x5.3 [cm]
Weight 31.3 [g]



8 007352 596146

Code 8007352596146
Quantity 20 NR
Dim. 21.4x11.6x6 [cm]
Weight 685.1 [g]

Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see [Conditions of Use](#).