



ARKÉ: Axial 1P 10AX 2-way switch white

19104.B

Wiring devices / Traditional wiring devices / ARKÉ / Devices

Axial 1P 10AX 2-way switch white

Axial 1P 10 AX 250 V~ 2-way switch, lightable, replaceable button, white. Max 100 W for lamps with built-in power unit (IEC 60669-1:2017)


Product Status

3 - Active


Minimum order quantity

20 NR


Drawings



Space view



Backside view



3D View



Technical data

- **Class group:** Domestic switching devices
- **Class:** Installation switch
- **Wiring system:** Two-way switch
- **Method of operation:** Rocker/button
- **Assembly arrangement:** Other
- **Number of modules (module system):** 1
- **Push button switch:** Yes
- **Number of rockers:** 0
- **Mounting method:** Flush-mounted
- **Type of fastening:** Engage (snap)
- **With mounting plate:** No
- **Material:** Plastic
- **Material quality:** Thermoplastic
- **Surface protection:** Untreated
- **Surface finishing:** Matt
- **Colour:** White
- **RAL-number (similar):** 9016
- **Label space/information surface:** Yes
- **Illumination:** Optional
- **Function lighting:** Control and orientation
- **Suitable for degree of protection (IP):** IP40
- **Nominal voltage:** 250 V
- **Rated current:** 10,00 A
- **Feedback-signal contact:** No
- **Connection type:** Screwed terminal
- **Washing machine switch:** No

Certifications

- 00. CE Marking - EU
- 01. IMQ - Italy ([download](#))
- 10. EAC Eurasian Customs Union
- 15. CCC - China ([download](#))
- 28. NSW - Australia ([download](#))
- 29. QCERT - Colombia
- 36. ISI - India
- 37. Marking - Morocco
- 43. UKCA mark - Great Britain
- 96. Electrotechnical expert ([download](#))
- 99. WEEE Directive ([download](#))

Packaging



Code 8007352684676
Quantity 1 NR
Dim. 5.1x2.8x5.3 [cm]
Weight 32.2 [g]



Code 8007352684683
Quantity 20 NR
Dim. 27x11.6x6 [cm]
Weight 709.4 [g]



Code 8007352684690
Quantity 120 NR
Dim. 37.5x30x13.5 [cm]
Weight 4,616.4 [g]

Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see [Conditions of Use](#).