



## ARKÉ: Univ.MASTER rotary-dimmer 230V Metal

### 19136.1.M

Wiring devices / Traditional wiring devices / ARKÉ / Devices

### Univ.MASTER rotary-dimmer 230V Metal

Universal-dimmer 230 V~ 50 Hz, phase-cutting, for: 40-400 W incandescent lamps, 40-300 VA electronic transformers, 10-200 W CFL lamps, 3-200 W LED lamps, LED phase-cutting electronic transformers, ON/OFF or built-in or from NO peripheral push buttons control, regulation by rotary potentiometer, MASTER function for 19137, minimum brightness regulation, visible in darkness, Metal. Not for Isoaset enclosures

### Product Status

3 - Active

### Minimum order quantity

10 NR


### Sheets, Manuals, Documentation

- [Multilanguage instructions sheet \(2356 kb\)](#)


### Video

- [Arké lives in your time](#)


### Drawings



Space view



Backside view



3D View



## Technical data

- **Class group:** Domestic switching devices
- **Class:** Dimmer
- **Method of operation:** Turn button
- **Mounting method:** Flush-mounted
- **Material:** Plastic
- **Material quality:** Thermoplastic
- **Surface protection:** Lacquered
- **Surface finishing:** Matt
- **Colour:** Aluminium
- **RAL-number (similar):** 9007
- **Transparent:** No
- **Nominal voltage:** 230,00 - 230,01 V
- **Connection type:** Screwed terminal
- **Device width:** 22,30 mm
- **Device height:** 49,00 mm
- **Device depth:** 50,70 mm

## Certifications

- 00. CE Marking - EU
- 31. TISI - Thailand
- 37. Marking - Morocco
- 43. UKCA mark - Great Britain
- 92. RoHS UAE
- 96. Electrotechnical expert ([download](#))
- 99. WEEE Directive ([download](#))

## Packaging



**Code** 8007352594227  
**Quantity** 1 NR  
**Dim.** 5.2x3.9x6.2 [cm]  
**Weight** 56 [g]



**Code** 8007352594234  
**Quantity** 10 NR  
**Dim.** 20.5x11.5x7 [cm]  
**Weight** 622.8 [g]

## Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see [Conditions of Use](#).