



## ARKÉ: SLAVE dimmer 120V grey

**19137.120**

Wiring devices / Traditional wiring devices / ARKÉ / Devices

### SLAVE dimmer 120V grey

SLAVE dimmer 120 V~ 60 Hz for: 40-500 W incandescent lamps, 40-300 VA electronic transformers, 10-200 W CFL lamps, 3-200 W LED lamps, control from MASTER CFL-LED-Dimmer with bleeder, visible in darkness, grey. Not for Isoset enclosures

### Product Status

2 - Will be discontinued

### Minimum order quantity

1 NR


### Sheets, Manuals, Documentation

- [FI - Foglio istruzioni ZIS\\_49400636A0 \(2838 kb\)](#)
- [SI - Schemi Installativi ZIS\\_120 V Insta \(2052 kb\)](#)


### Video

- [Arké lives in your time](#)


### Drawings



Space view



Backside view



3D View



## Technical data

- **Class group:** Domestic switching devices
- **Class:** Dimmer
- **Method of operation:** Other
- **Type of load:** Universal and LED Retrofit
- **Applicable with button:** No
- **Applicable with movement sensor:** No
- **Applicable with presence indicator:** No
- **Applicable with time switch/timer:** No
- **Applicable with transmission button:** No
- **Applicable with infrared button:** No
- **Mounting method:** Flush-mounted
- **Type of fastening:** Snapper mounting
- **Material:** Plastic
- **Material quality:** Thermoplastic
- **Surface protection:** Untreated
- **Surface finishing:** Matt
- **Colour:** Grey
- **RAL-number (similar):** 7015
- **Transparent:** No
- **Suitable for degree of protection (IP):** IP40
- **Nominal voltage:** 120,00 - 120,01 V
- **Frequency:** 60,00 - 60,01 HZ
- **Control voltage:** 120,00 - 120,01 V
- **Device width:** 22,30 mm
- **Device height:** 49,00 mm
- **Device depth:** 51,00 mm

## Certifications

- 37. Marking - Morocco

## Packaging



**Code** 8007352498006  
**Quantity** 1 NR  
**Dim.** 5.1x4.3x5.3 [cm]  
**Weight** 57.6 [g]

**Code** 8007352498013  
**Quantity** 5 NR  
**Dim.** 14.4x11.6x6 [cm]  
**Weight** 336.9 [g]

## Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see [Conditions of Use](#).