



ARKÉ: IR relay-switch 120V Metal

19181.120.M

Wiring devices / Traditional wiring devices / ARKÉ / Devices

IR relay-switch 120V Metal

Automatic lighting switch with IR motion sensor, adjustable dusk/dawn sensor threshold and time-delay cycle, NO 6 A 120 V~ relay output, supply voltage 120 V~ 50-60 Hz, Metal

Product Status

3 - Active

Minimum order quantity

5 NR


Sheets, Manuals, Documentation

- [Light Multilanguage instructions sheet \(834 kb\)](#)
- [Full Multilanguage instructions sheet \(859 kb\)](#)


Video

- [Arké lives in your time](#)


Drawings



Space view



Backside view



3D View



Technical data

- **Class group:** Domestic switching devices
- **Class:** Electronic insert for domestic switching devices
- **Model:** Other
- **Assembly arrangement:** Modular device for domestic switching devices
- **Number of modules (module system):** 1
- **Radio-controlled:** No
- **Mounting method:** Flush-mounted
- **Type of fastening:** Engage (snap)
- **Material:** Plastic
- **Material quality:** Thermoplastic
- **Surface protection:** Lacquered
- **Surface finishing:** Matt
- **Colour:** Aluminium
- **RAL-number (similar):** 9007
- **Transparent:** No

Certifications

- 00. CE Marking - EU
- 19. NOM - Mexico
- 37. Marking - Morocco
- 43. UKCA mark - Great Britain
- 96. Electrotechnical expert ([download](#))
- 99. WEEE Directive ([download](#))

Packaging



Code 8007352594203
Quantity 1 NR
Dim. 5.1x4.3x5.3 [cm]
Weight 51.4 [g]

Code 8007352594210
Quantity 5 NR
Dim. 14.4x11.6x6 [cm]
Weight 307 [g]

Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see [Conditions of Use](#).