



# ARKÉ: Two 2P+E 15A USA outlet with GFCI grey

#### 19296

Wiring devices / Traditional wiring devices / ARKÉ / Devices

### Two 2P+E 15A USA outlet with GFCI grey

Double 2P+E 15 A 125 V~ 60 Hz socket outlet, American standard with GFCI, built-in mounting frame, to complete with 3-module cover plate, grey

#### **Product Status**

3 - Active

#### Minimum order quantity

5 NR

#### Sheets, Manuals, Documentation

Multilanguage instructions sheet (450 kb)

#### Video

• Arké lives in your time

# Drawings



### Technical data

Class group: Domestic switching devices

Class: Socket outlet

Number of modules (module system): 3

Number of socket outlets switchable: 0

Imprint/indication: None

Connection type: Screwed terminal

With hinged lid: No

With enhanced contact protection: No

Label space/information surface: Yes

Colour: Grey

RAL-number (similar): 7015

Metallic colour: No Transparent: No Lockable: No

Eject-mechanism: No **Insulated mounting: No** 

With function lighting: Yes With orientation lighting: No

Over voltage protection: No

Fault current protection: Yes

With miniature fuse: No

Mounting method: Flush-mounted Type of fastening: Mounting with screw

Material: Plastic

Material quality: Thermoplastic

Halogen free: Yes

Surface protection: Untreated

Surface finishing: Matt

With loop through function: No

With on/off switch: No Rotated central insert: No Nominal current: 15 A Nominal voltage: 125 V Frequency: 60,00 - 60,01 HZ Rated fault current: 6 mA

Suitable for degree of protection (IP): IP20

Impact strength: Other Device width: 73,00 mm Device height: 107,00 mm Device depth: 41,10 mm

### Certifications

00. CE Marking - EU

19. NOM - Mexico

29. QCERT - Colombia (download)

37. Marking - Morocco

# Packaging



Code Quantity Dim.

8007352471825 1 NR

6.7x5.2x12 [cm]

Weight 163.5 [g]

Code Quantity

5 NR 29.5x13.5x7.7 [cm] Dim.

8007352471832

Weight 892.5 [g]



Code Quantity Dim.

8007352471849 95 NR

55.5x37.5x29 [cm] Weight 17,837.5 [g]

# Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see Conditions of Use.