



ARKÉ: Bell/buzzer 12V 50-60Hz Metal

19370.SR.M

Wiring devices / Traditional wiring devices / ARKÉ / Devices

Bell/buzzer 12V 50-60Hz Metal

Product Status

3 - Active


Minimum order quantity

10 NR


Sheets, Manuals, Documentation

- [Multilanguage instructions sheet \(711 kb\)](#)


Drawings



Space view



Backside view



3D View



Technical data

- **Class group:** Optical and acoustic signalling equipment
- **Class:** Bell
- **Housing colour:** Aluminium
- **Nominal voltage:** 12,00 - 12,01 V
- **Degree of protection (IP):** IP40
- **Type of current:** AC
- **Built-in battery:** No
- **Mounting method:** Flush-mounted
- **Wireless:** No

Certifications

- 00. CE Marking - EU
- 10. EAC Eurasian Customs Union
- 43. UKCA mark - Great Britain
- 99. WEEE Directive ([download](#))

Packaging



Code 8007352739918
Quantity 1 NR
Dim. 4.6x2.7x5.6 [cm]
Weight 43.4 [g]



Code 8007352739925
Quantity 10 NR
Dim. 14.8x10x6.8 [cm]
Weight 481.34 [g]



Code 8007352739932
Quantity 120 NR
Dim. 31x22x21 [cm]
Weight 6,023.6 [g]

Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see [Conditions of Use](#).