



## ARKÉ: Bell/buzzer 120V 50-60Hz Metal

**19372.SR.M**

Wiring devices / Traditional wiring devices / ARKÉ / Devices

**Bell/buzzer 120V 50-60Hz Metal**

### Product Status


3 - Active

### Minimum order quantity


10 NR




### Drawings



Space view



Backside view



3D View

### Technical data

- **Class group:** Optical and acoustic signalling equipment
- **Class:** Bell
- **Housing colour:** Aluminium
- **Nominal voltage:** 120,00 - 120,01 V
- **Degree of protection (IP):** IP40
- **Type of current:** AC
- **Built-in battery:** No
- **Mounting method:** Flush-mounted
- **Wireless:** No

### Certifications


- 00. CE Marking - EU
- 96. Electrotechnical expert ([download](#))
- 99. WEEE Directive ([download](#))

## Packaging



8 007352740006

**Code** 8007352740006  
**Quantity** 1 NR  
**Dim.** 4.6x2.7x5.6 [cm]  
**Weight** 43.22 [g]



8 007352740013

**Code** 8007352740013  
**Quantity** 10 NR  
**Dim.** 14.8x10x6.8 [cm]  
**Weight** 480.57 [g]



8 007352740020

**Code** 8007352740020  
**Quantity** 120 NR  
**Dim.** 31x22x21 [cm]  
**Weight** 6,014.84 [g]

## Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see [Conditions of Use](#).